



Easy series

EasyPactTM CVS

Catalog 2021

Molded-case circuit breakers and
switch-disconnectors from 16 to 630A



<https://www.se.com>

Life Is On

Schneider
 Electric



Green Premium™

An industry leading portfolio of offers delivering sustainable value



More than 75% of our product sales offer superior transparency on the material content, regulatory information and environmental impact of our products:

- RoHS compliance
- REACH substance information
- Industry leading # of PEP's*
- Circularity instructions



Discover what we mean by green
Check your products!

The Green Premium program stands for our commitment to deliver customer valued sustainable performance. It has been upgraded with recognized environmental claims and extended to cover all offers including Products, Services and Solutions.

CO₂ and P&L impact through... Resource Performance

Green Premium brings improved resource efficiency throughout an asset's lifecycle. This includes efficient use of energy and natural resources, along with the minimization of CO₂ emissions.

Cost of ownership optimization through... Circular Performance

We're helping our customers optimize the total cost of ownership of their assets. To do this, we provide IoT-enabled solutions, as well as upgrade, repair, retrofit, and remanufacture services.

Peace of mind through... Well-being Performance

Green Premium products are RoHS and REACH compliant. We're going beyond regulatory compliance with step-by-step substitution of certain materials and substances from our products.

Improved sales through... Differentiation

Green Premium delivers strong value propositions through third-party labels and services. By collaborating with third-party organizations we can support our customers in meeting their sustainability goals such as green building certifications.

Easy choice for Quality and Value



EasyPact CVS is...Safe

Isolation

- EasyPact CVS circuit breakers are suitable for Isolation as defined in IEC standards 60947-2. The aim of isolation is to separate a circuit or apparatus from the remainder of a system which is energized in order that personnel may carry out work on the isolated part in perfect safety.
- MCCB locking with external padlocks enables a user to isolate and undertake maintenance with utmost safety.



Isolation




Locking in OFF position

- Key locks enable to lock the breaker in OFF position ensuring safety and better control on installation.
- It also helps in interlocking multiple circuit breakers in an installation.




Class II front Face

- All EasyPact CVS MCCBs are class II Front face devices, they may be installed through the door of class II switchboards without downgrading the switchboard insulation. Installation requires no special operation, even when the Circuit Breaker is equipped with a rotary handle.



Class II panel with circuit breaker having a class II front face





EasyPact CVS is...Reliable



Conforms to IEC 60947-2 for circuit breaker

- Tested at renown international laboratories like KEMA
- Complete range with $I_{cs} = 100\% I_{cu}$



High electrical & Mechanical endurance

- 30000 mechanical operations for 100A
- 12000 electrical operations for 100A



Reliable accessories

- Continuous rated shunt coils
- Multifunctional Aux./Alarm contact
- Unique electrical fault trip indication (SDE)




EasyPact CVS offer protection for human as well as Electrical installation


- Earth leakage protection through Vigi Module to protect human against leakage current


Fault current limitation technology

- EasyPact CVS Double break mechanism ensures high fault current limitation
 - @ Reduces thermal stresses on the electrical distribution network
 - @ Increases the life of cables and installation



EasyPact CVS Double break Roto mechanism






EasyPact CVS is...Simple

Only two frame sizes
up to 630A

Frame - I 100 - 250A
Frame - II 400 - 630A

- Common and snap-fit accessories up to 630A
- Single OF contact for ON/OFF, Trip indication
- Single Shunt coil for remote tripping
- Single Under Voltage coil

- Easypact CVS share same footprint of Compact Family MCCBs.
 - mounting dimensions
 - easy retrofitting
 - system upgradeability



EasyPact CVS stands for customer value

EasyPact CVS 100 to 630 A



Panel builders

- Only two frame sizes up to 630A
- Common accessories for complete range (ON/OFF/Trip Auxiliaries/Shunt/UV etc)
- Line load reversibility for entire range
- Suitable for class II switchboards




End Users

- Isolation as a standard feature enhances safety
- Excellent current limiting capability reduces stresses on cables, busbars and loads
- Continuous rated accessories increase system reliability
- Modular earth leakage protection ensure human/installation protection



OEMs

- High endurance's and maintenance-free operation assure continuous performance of machines
- Unique common accessories help standardisation of components



Contractors

- Sufficient pole pitch helps to terminate Copper and Aluminum busbars or cables
- Easy availability of the product due to less number of frame size
- Designed to perform in demanding applications

- > Do you strain to find circuit breakers that are simple as well as flexible and safe?
- > Has it been difficult to find high quality circuit breakers at the right price point?
- > Do you need the reach, support and accessibility of a global leader, with the value of a local supplier?



Buildings



Industry

Gain peace of mind,
quality, and value for
your installations



General contents

EasyPact™ CVS

Presentation

1

Functions
and characteristics

A-1

Installation
recommendations

B-1

Dimensions
and connection

C-1

Additional characteristics

D-1

Catalogue numbers

E-1

EasyPact CVS100BS


F-1

Functions and characteristics



Functions and characteristics

| | |
|--|-------------|
| Introduction | A-2 |
| General characteristics | A-2 |
| Characteristics and performance | A-4 |
| | |
| Protection of distribution systems | A-6 |
| TM-D thermal-magnetic trip units | A-6 |
| TM-G thermal-magnetic trip units | A-7 |
| ETS 2.3 electronic trip unit and accessories | A-8 |
| | |
| Earth-leakage protection | A-9 |
| | |
| Motor protection | A-11 |
| MA instantaneous trip units | A-11 |
| | |
| Switch-disconnectors | A-12 |
| | |
| Accessories and auxiliaries | A-14 |
| Overview | A-14 |
| Device installation | A-15 |
| Connection of devices | A-16 |
| Selection of auxiliaries | A-18 |
| Indication contacts | A-19 |
| Remote tripping | A-20 |
| Rotary handles | A-21 |
| Locks and sealing accessories | A-22 |
| Escutcheons and protection collars | A-23 |
| | |
| <i>Installation recommendations</i> | <i>B-1</i> |
| <i>Dimensions and connection</i> | <i>C-1</i> |
| <i>Additional characteristics</i> | <i>D-1</i> |
| <i>Catalogue numbers</i> | <i>E-1</i> |
| <i>CVS100BS</i> | <i>F-1</i> |



Standardised characteristics indicated on the rating plate:

- 1 Type of device: frame size and breaking capacity class
- 2 Ui : rated insulation voltage.
- 3 U_{imp} : rated impulse withstand voltage.
- 4 I_{cs} : service breaking capacity.
- 5 I_{cu} : ultimate breaking capacity for various values of the rated operational voltage U_e
- 6 U_e : operational voltage.
- 7 Suitable for Isolation symbol.
- 8 Reference standard.

Note: when the circuit breaker is equipped with an extended rotary handle, the door must be opened to access the rating plate.

Compliance with standards

EasyPact CVS circuit breakers and auxiliaries comply with the following international recommendations:

- IEC 60947-1: general rules
- IEC 60947-2: circuit breakers
- IEC 60947-3: switch-disconnectors

Pollution degree

EasyPact CVS circuit breakers are certified for operation in pollution-degree III environments as defined by IEC standards 60947-1 and 60664-1 (industrial environments).

Climatic withstand

EasyPact CVS circuit breakers have successfully passed the tests defined by the following standards for extreme atmospheric conditions:

- IEC 60068-2-1: dry cold (-55°C)
- IEC 60068-2-2: dry heat (+85°C)
- IEC 60068-2-30: damp heat (95 % relative humidity at 55°C)
- IEC 60068-2-52 severity level 2: salt mist.

Environment

EasyPact CVS respects the European environment directive EC/2002/95 concerning the restriction of hazardous substances (RoHS).

All EasyPact CVS production sites have set up an ISO 14001 certified environmental management system.

Ambient temperature

- EasyPact CVS circuit breakers can be used between -25°C and +70°C. For temperatures higher than 40°C (65°C for circuit breakers used to protect motor feeders), devices must be derated ([see page B-2](#)).
- Circuit breakers should be put into service under normal ambient, operating-temperature conditions. Exceptionally, the circuit breaker can be put into service when the ambient temperature is between -35°C and -25°C.
- The permissible storage-temperature range for EasyPact CVS circuit breakers in the original packing is -50°C and +85°C.

Electromagnetic compatibility

EasyPact CVS circuit breakers with ETS2.3 electronic trip unit have successfully passed the tests defined by the following standards for EMC:


- IEC/EN 60947-2, Annex F: Immunity tests for circuit breakers with electronic protection

Suitable for isolation with positive contact indication


All EasyPact CVS circuit breakers are suitable for isolation as defined in IEC standard 60947-2:

- The isolation position corresponds to the O (OFF) position.
 - The operating handle cannot indicate the OFF position unless the contacts are effectively open.
 - Padlocks cannot be installed unless the contacts are open.
- Installation of a rotary handle does not alter the reliability of the position-indication system.
- The isolation function is certified by tests guaranteeing:
- The mechanical reliability of the position-indication system
 - The absence of leakage currents
 - Over voltage withstand capacity between upstream and downstream connections.


The tripped position does not ensure isolation with positive contact indication.
Only the OFF position guarantees isolation.




**EasyPact CVS100/160/250/400/630
with terminal shields**




EasyPact CVS100/160/250




**EasyPact CVS100/160/250
with direct rotary handle**




EasyPact CVS100/160/250 with extended rotary handle



EasyPact CVS400/630



**EasyPact CVS400/630 with
direct rotary handle**



EasyPact CVS400/630 with extended rotary handle

Installation in class II switchboards

All EasyPact CVS circuit breakers are class II front face devices. They can be installed through the door of class II switchboards (as per IEC standards 61140 and 60664-1) without downgrading switchboard insulation. Installation requires no special operations, even when the circuit breaker is equipped with a rotary handle.

Degree of protection

The following indications are in accordance with standards IEC 60529 (IP degree of protection) and IEC 62262 (IK protection against external mechanical impacts).

Bare circuit breaker with Escutcheon:

- with toggle: IP40, IK07 front face
- with extended rotary handle: IP 54, IK08

Circuit breaker installed in a switchboard:

- with toggle: IP40, IK07 front face
- with extended rotary handle: IP 54, IK08

Protection degree

Protection degree of the product, according to IEC60259, depends on its configuration:

| Colours | Definition |
|------------|---|
| Green | IP54: front extended rotary handle |
| Light Blue | IP40: front cover, side, back, terminal shield, direct rotary handle |
| Yellow | IP20: power connection cover |
| Orange | maybe IP20 or less depending on the kind of power connections and cable size used |
| Legend: | |
| Green | IP54 |
| Light Blue | IP40 |
| Yellow | IP20 |
| Orange | < IP20 |

PB106447



EasyPact CVS100/160/250

PB106448



EasyPact CVS400/630

Common characteristics

Rated voltages

| | | |
|--------------------------------|-------------|--------------------|
| Insulation voltage (V) | Ui | 690 |
| Impulse withstand voltage (kV) | Uimp | 8 |
| Operational voltage (V) | Ue | AC 50/60 Hz 440 |
| Suitability for isolation | | IEC/EN 60947-2 yes |
| Utilisation category | | A |
| Pollution degree | | IEC 60664-1 3 |

Circuit breakers

Performance

Electrical characteristics as per IEC 60947-2

| | | |
|-------------------|-----------|-------|
| Rated current (A) | In | 40 °C |
|-------------------|-----------|-------|

Number of poles

Breaking capacity levels

Breaking capacity (kA rms)

| | | |
|------------|-------------|---------------------------------|
| Icu | AC 50/60 Hz | 220/240 V 380/415 V 440 V |
|------------|-------------|---------------------------------|

Service breaking capacity (kA rms)

| | | |
|------------|-------------|---------------------------------|
| Ics | AC 50/60 Hz | 220/240 V 380/415 V 440 V |
|------------|-------------|---------------------------------|

Durability (C-O cycles)

| | | |
|------------|------|------|
| Mechanical | | |
| Electrical | 415V | In/2 |

Protection

Short-circuit protection

Magnetic only

Overload/short-circuit protection

Thermal magnetic

Electronic

with neutral protection (Off-0.5-1)

Earth-leakage protection

By Vigi module

Installation/connections

Dimensions and weights

| | | |
|------------------------------|--------------------------|----------|
| Dimensions (mm) W x H x D | Fixed, front connections | 3P 4P |
| Weight (kg) | Fixed, front connections | 3P 4P |

Connections

| | | |
|-----------------------|---------------|----------------------------|
| Connection terminals | Pitch | Without/ With spreaders |
| Large Cu or Al cables | Cross-section | mm ² |


| CVS100 | | | CVS160 | | | CVS250 | | | CVS400 | | | CVS630 | | |
|----------------|------|------|----------------|------|------|----------------|------|------|-----------------|------|-----------------|--------|------|------|
| 100 | | | 160 | | | 250 | | | 400 | | | 630 | | |
| 3, 4 | 3, 4 | 3, 4 | 3, 4 | 3, 4 | 3, 4 | 3, 4 | 3, 4 | 3, 4 | 3, 4 | 3, 4 | 3, 4 | 3, 4 | 3, 4 | 3, 4 |
| B | F | N | B | F | N | B | F | N | F | N | F | F | N | N |
| 40 | 70 | 90 | 40 | 70 | 90 | 40 | 70 | 90 | 40 | 70 | 40 | 70 | | |
| 25 | 36 | 50 | 25 | 36 | 50 | 25 | 36 | 50 | 36 | 50 | 36 | 50 | | |
| 20 | 36 | 50 | 20 | 36 | 50 | 20 | 36 | 50 | 30 | 42 | 30 | 42 | | |
| 40 | 70 | 90 | 40 | 70 | 90 | 40 | 70 | 90 | 40 | 70 | 40 | 70 | | |
| 25 | 36 | 50 | 25 | 36 | 50 | 25 | 36 | 50 | 36 | 50 | 36 | 50 | | |
| 15 | 18 | 38 | 15 | 18 | 38 | 15 | 18 | 38 | 23 | 32 | 23 | 32 | | |
| 30000 | | | 25000 | | | 20000 | | | 15000 | | 15000 | | | |
| 30000 | | | 25000 | | | 20000 | | | 12000 | | 8000 | | | |
| 12000 | | | 12000 | | | 10000 | | | 6000 | | 4000 | | | |
| ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ |
| ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ |
| - | - | - | - | - | - | - | - | - | - | - | - | - | - | - |
| ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ |
| 105 x 161 x 86 | | | 105 x 161 x 86 | | | 105 x 161 x 86 | | | 140 x 255 x 110 | | 140 x 255 x 110 | | | |
| 140 x 161 x 86 | | | 140 x 161 x 86 | | | 140 x 161 x 86 | | | 185 x 255 x 110 | | 185 x 255 x 110 | | | |
| 1.8 | | | 1.8 | | | 2.0 | | | 4.7 | | 5.2 | | | |
| 2.2 | | | 2.3 | | | 2.6 | | | 6.3 | | 7.1 | | | |
| 35/45 mm | | | 35/45 mm | | | 35/45 mm | | | 45/52.5 mm | | 45/52.5 mm | | | |
| 300 | | | 300 | | | 300 | | | 45/70 mm | | 45/70 mm | | | |
| | | | | | | | | | 4 x 240 | | 4 x 240 | | | |

Protection of distribution systems

TM-D thermal-magnetic trip units

TM-D thermal-magnetic trip units can be used on EasyPact CVS100-630 circuit breakers with performance levels B/F/N.

TM-D thermal-magnetic trip units



Protection



TM-D trip units are used mainly in electrical distribution applications for protection of cables supplied by transformers.

Thermal protection (Ir)

Thermal protection operates according to:

- Ir that can be adjusted in amps from 0.7 to 1 times the rating of the trip unit (16 A to 250 A), corresponding to settings from 11 to 250 A for the range of trip units
- a non-adjustable time delay.

Magnetic protection (Im)

Short-circuit protection with a fixed or adjustable pick-up Im that initiates instantaneous tripping if exceeded.

- TM-D: fixed pick-up, Im, for 16 to 250 A ratings and adjustable from 5 to 10 x In for 400 A ratings, 4.2 to 8.3 x In for 600 A rating.

Protection versions

- 3-pole:
- 3P 3D: 3-pole frame (3P) with detection on all 3 poles (3D)
- 4-pole:
- 4P 3D: 4-pole frame (4P) with detection on 3 poles (3D).
- 4P 4D: 4-pole frame (4P) with detection on all 4 poles (same threshold for phases and neutral).


| Thermal-magnetic trip units | | TM16D to 250D | | | | | | | | | | | | TM320D to 600D | | | |
|---|----------------------------|---------------------|-------|--------------|-----|-----|-----|-----|-----|-----|------|------|------|--|-----|-----|-----|
| Ratings (A) | In at 40 °C ⁽¹⁾ | 16 | 25 | 32 | 40 | 50 | 63 | 80 | 100 | 125 | 160 | 200 | 250 | 320 | 400 | 500 | 600 |
| Circuit breaker | CVS100 | ■ | ■ | ■ | ■ | ■ | ■ | ■ | ■ | - | - | - | - | - | - | - | - |
| | CVS160 | - | - | - | - | - | - | - | ■ | ■ | ■ | ■ | - | - | - | - | - |
| | CVS250 | - | - | - | - | - | - | - | - | ■ | ■ | ■ | ■ | - | - | - | - |
| | CVS400 | - | - | - | - | - | - | - | - | ■ | ■ | ■ | ■ | - | - | - | - |
| | CVS630 | - | - | - | - | - | - | - | - | - | ■ | ■ | ■ | - | - | - | - |
| Magnetic protection | | fixed | | | | | | | | | | | | adjustable | | | |
| Pick-up (A) accuracy ±20 % | Im | 190 | 300 | 400 | 500 | 500 | 500 | 640 | 800 | | | | | 1600 to 3200 (320A), 2000 to 4000 (400A) | | | |
| | CVS100 | | | | | | | | | 800 | 1250 | 1250 | 2000 | 2500 | | | |
| | CVS160/250 | | | | | | | | | | | | | | | | |
| | CVS400 | | | | | | | | | | | | | | | | |
| | CVS630 | | | | | | | | | | | | | | | | |
| Thermal protection | | Ir = In x ... | | | | | | | | | | | | adjustable in amps from 0.7 to 1 x In | | | |
| Pick-up (A) tripping between 1.05 and 1.30 Ir | | | | | | | | | | | | | | | | | |
| Neutral protection | | Unprotected neutral | 4P 3D | no detection | | | | | | | | | | | | | |
| Fully protected neutral | 4P 4D | | | 1 x Ir | | | | | | | | | | | | | |

⁽¹⁾ For temperatures not equal to 40°C, the thermal protection characteristics are modified. See the temperature derating table on page B-2.

Note: All the trip units have a transparent lead-sealable cover that protects access to the adjustment dials.

TM-G thermal-magnetic trip units can be used on EasyPact CVS160-250 circuit breakers with performance levels B for the protection of generators or long cable length.

TM-G thermal-magnetic trip units



Protection

TM-G, with a low pick-up for generators (lower short-circuit currents than with transformers) and distribution system with long cable lengths (fault current limited by impedance of the cable).

Thermal protection (Ir)

Thermal protection operates according to:

- Ir that can be adjusted in amps from 0.7 to 1 times the rating of the trip unit (80 A to 250 A), corresponding to settings from 56 to 250 A for the range of trip units
- a non-adjustable time delay.

Magnetic protection (Im)

Short-circuit protection with a fixed Im that initiates instantaneous tripping if exceeded.

- TM-G: fixed pick-up, Im, for 80 to 250 A ratings.

Protection versions


- 3-pole:
- 3P 3D: 3-pole frame (3P) with detection on all 3 poles (3D)
- 4-pole:
- 4P 3D: 4-pole frame (4P) with detection on 3 poles (3D).

| Thermal-magnetic trip units | | TM80G to 250G | | | | | |
|---|----------------------------|---------------------------------------|-----|-----|-----|-----|-----|
| Ratings (A) | In at 40 °C ⁽¹⁾ | 80 | 100 | 125 | 160 | 200 | 250 |
| Circuit breaker | CVS160 | ■ | ■ | ■ | ■ | - | - |
| | CVS250 | - | - | - | - | ■ | ■ |
| Magnetic protection | | | | | | | |
| Pick-up (A) | Im | | | | | | |
| accuracy ±20 % | CVS160/250 | 200 | 320 | 440 | 500 | 600 | 750 |
| Thermal protection | | | | | | | |
| Pick-up (A) tripping between 1.05 and 1.30 Ir | Ir = In x ... | adjustable in amps from 0.7 to 1 x In | | | | | |
| Neutral protection | | | | | | | |
| Unprotected neutral | 4P 3D | no detection | | | | | |

Protection of distribution systems

ETS 2.3 electronic trip unit and accessories

ETS2.3 electronic trip unit



Circuit breakers equipped with ETS2.3 trip units can be used to protect distribution systems supplied by transformers.

Protection



Settings are made using the adjustment dials with adjustment possibilities.

Overloads: Long time protection (Ir)

Inverse time protection against overloads with an adjustable current pick-up Ir set using a dial and a non-adjustable time delay tr .

Short-circuits: Short-time protection with fixed time delay (Istd)


Protection with an adjustable pick-up $Istd$. Tripping takes place after a very short delay used to allow discrimination with the downstream device.

Short-circuits: Non-adjustable instantaneous protection

Instantaneous short-circuit protection with a fixed pick-up.

Neutral protection


- On 3-pole circuit breakers, neutral protection is not possible.
- On four-pole circuit breakers, neutral protection may be set using a three-position switch:
 - 4P 3D: neutral unprotected
 - 4P 3D + N/2: neutral protection at half the value of the phase pick-up, i.e. $0.5 \times Ir$
 - 4P 4D: neutral fully protected at Ir



Note: all the trip units have a transparent lead-sealable cover that protects access to the adjustment dials.

ETS2.3

| Ratings (A) | In at 40 °C ⁽¹⁾ | 400 | 630 |
|--|--------------------------------------|---|--|
| Circuit breaker | EasyPact CVS400 | ■ | - |
| | EasyPact CVS630 | - | ■ |
| L Long-time protection | | | |
| Pick-up (A) | | | |
| tripping between 1.05 and 1.20 Ir | $Ir =$ $In = 400 A$ | $Ir =$ $160 \quad 180 \quad 200 \quad 230 \quad 250 \quad 280 \quad 320 \quad 360 \quad 400$ | value depending on trip unit rating (In) and setting on dial |
| | $In = 630 A$ | $Ir =$ $250 \quad 280 \quad 315 \quad 370 \quad 400 \quad 440 \quad 505 \quad 565 \quad 630$ | |
| Time delay (s) | tr | keypad setting | non-adjustable |
| accuracy 0 to -20 % | | $1.5 \times Ir$ $6 \times Ir$ $7.2 \times Ir$ | 200 8 5.5 |
| Thermal memory | 20 minutes before and after tripping | | |
| S₀ Short-time protection with fixed time delay | | | |
| Pick-up (A) | $Istd = Ir \times ...$ | 1.5 2 3 4 5 6 7 8 10 | |
| accuracy $\pm 10\%$ | | | |
| | tsd | non-adjustable | |
| | Non-tripping time | 20 | |
| | Maximum break time | 80 | |
| I Instantaneous protection | | | |
| Pick-up (A) | li non-adjustable | 4800 6930 | |
| accuracy $\pm 15\%$ | Non-tripping time | 10 ms | |
| | Maximum break time | 50 ms for $I > li$ | |



(1) If the trip units are used in high-temperature environments, the ETS2.3 setting must take into account the thermal limitations of the circuit breaker. See the temperature derating table.

Earth-leakage protection

Add-on protection against insulation faults using a Vigi module

A Vigi module can be added to any three or four-pole CVS100 to 630 circuit breaker to form a Vigi CVS.

PB108449



Vigi CVS100 to 630

Circuit breaker with add-on Vigi module (Vigi CVS)

- For general characteristics of circuit breakers, see pages A-2 and A-3.
- Add-on Vigi modules: Earth-leakage protection is achieved by installing a Vigi module (characteristics and selection criteria on next page) directly on the circuit breaker terminals. It directly actuates the trip unit (magnetic, thermal-magnetic or ETS).

Vigi CVS100 to 630 circuit breakers with earth-leakage protection

Addition of the Vigi module does not alter circuit-breaker characteristics:

- compliance with standards
- degree of protection, class II front-face insulation
- positive contact indication
- electrical characteristics
- trip-unit characteristics
- installation and connection modes
- indication, measurement and control auxiliaries
- installation and connection accessories.

| Dimensions and weights | CVS100/160/250 | CVS400/630 |
|------------------------|----------------|-----------------|
| Dimensions | 3-pole | 105 x 236 x 86 |
| | 4-pole | 140 x 236 x 86 |
| W x H x D (mm) | | 185 x 355 x 110 |
| Weight (kg) | 3-pole | 2.5 |
| | 4-pole | 3.2 |
| | | 8.8 |
| | | 10.8 |

PB103590-36




Vigi earth-leakage protection modules

Compliance with standards

- IEC 60947-2, annex B.
- Decree dated 14 November 1988 (for France).
- IEC 60755, class A, immunity to DC components up to 6 mA
- operation down to -25 °C as per VDE 664.

DB112147



- 1 Sensitivity setting
- 2 Time-delay setting (for selective earth-leakage protection).
- 3 Lead-seal fixture for controlled access to settings.
- 4 Test button simulating an earth-fault for regular checks on the tripping function
- 5 Reset button (reset required after earth-fault tripping).
- 6 Rating plate

Vigi module selection


| Type | CVS100/160/250 | CVS400/630 |
|-----------------------------------|---|------------------------|
| Number of poles | 3, 4 ⁽¹⁾ | 3, 4 ⁽¹⁾ |
| Protection characteristics | | |
| Sensitivity | adjustable | adjustable |
| IΔn (A) | 0.03 - 0.3 - 1 - 3 - 10 | 0.3 - 1 - 3 - 10 - 30 |
| Time delay | adjustable | adjustable |
| Intentional delay (ms) | 0 - 60 ⁽²⁾ - 150 ⁽²⁾ - 300 ⁽²⁾ | 0 - 60 - 150 - 300 |
| Max. break time (ms) | < 40 < 140 < 300 < 800 | < 40 < 140 < 300 < 800 |
| Rated voltage V AC 50/60 Hz | 200...440 | 200...440 |

(1) Vigi 3P modules may also be used on 3P circuit breakers used for two-phase protection.
(2) If the sensitivity is set to 30 mA, there is no time delay, whatever the time-delay setting.


Operating safety

The Vigi module is a user safety device. It must be tested at regular intervals (every 6 months) via the test button.

MA magnetic trip units for EasyPact CVS100-630A



Circuit breakers with an MA trip unit are combined with a thermal relay and a contactor or a starter.



Protection



Magnetic protection (I_m)

Short-circuit protection with an adjustable pick-up I_m that initiates instantaneous tripping if exceeded.

- $I_m = I_n \times \dots$ is set on an adjustment dial in multiples of the rating:

- 6 to $14 \times I_n$ (2.5 to 100 A ratings)
- 9 to $14 \times I_n$ (150 to 220 A ratings)
- 6 to $13 \times I_n$ (320 to 500 A ratings)

Protection version

- 3-pole (3P 3D): 3-pole frame (3P) equipped with detection on all 3 poles (3D).

Motor protection up to 250 kW

| Motor protection rating (kW) | | | |
|--|-----------|----------|------------|
| CVS 100/160/250 | 1.1...110 | | 18.5...250 |
| CVS 400/630 | | | |
| Breaking capacity (kA rms) 380/415V | B F | 25 36 | - 36 |
| | N | 50 | 50 |

CVS100 to 630 circuit breakers, equipped with an MA magnetic trip unit with adjustable thresholds, offer:

- short-circuit protection
- suitability for isolation.

CVS100 to 630 circuit breakers with trip unit are supplied ready-assembled.

MA trip units

| Ratings (A) | In at 65 °C | 2.5 | 6.3 | 12.5 | 25 | 50 | 100 | 150 | 220 | 320 | 500 |
|-----------------|-------------|-----|-----|------|----|----|-----|-----|-----|-----|-----|
| Circuit breaker | CVS100 | ■ | ■ | ■ | ■ | ■ | ■ | - | - | - | - |
| | CVS160 | - | - | - | - | - | ■ | ■ | - | - | - |
| | CVS250 | - | - | - | - | - | ■ | ■ | - | - | - |
| | CVS400 | - | - | - | - | - | - | - | ■ | - | - |
| | CVS630 | - | - | - | - | - | - | - | - | ■ | - |

Short-circuit protection (magnetic)

| Pick-up (A) | $I_m = I_n \times \dots$ | setting 6...14 x I_n | setting 9...14 x I_n | setting 6...13 x I_n |
|-------------|--------------------------|---------------------------|---------------------------|---------------------------|
| CVS100 | - | - | - | - |
| CVS160/250 | - | - | - | - |
| CVS400/630 | - | - | - | - |

Installation standards require upstream protection.
However EasyPact CVS100 to 630 NA switch-disconnectors are self-protected by their high-set magnetic release.

PB106451



EasyPact CVS100 to 250 NA

PB106452



EasyPact CVS400 to 630 NA

Switch-disconnectors

Electrical characteristics as per IEC 60947-3 and EN 60947-3

Conventional thermal current (A) I_{th} 50 °C

Number of poles

Operational current (A) depending on the utilisation category I_e AC 50/60 Hz

220/240 V

380/415 V

440 V

Short-circuit making capacity (kA peak) I_{cm} min. (switch-disconnector alone)
max. (protection by upstream circuit breaker)

Rated short-time withstand current (A rms) I_{cw} for 1 s
3 s
20 s

Durability (C-O cycles) mechanical
electrical AC

415 V

In

Protection

Add-on earth-leakage protection By Vigi module

Additional indication and control auxiliaries

Indication contacts

Voltage releases MX shunt release
MN undervoltage release

Installation/connections

Dimensions (mm) fixed, front connections 3P

W x H x D 4P



Weight (kg) fixed, front connections 3P

4P


| CVS100NA | CVS160NA | CVS250NA | CVS400NA | CVS630NA |
|--|---------------|--|---------------|---------------|
| 100 3, 4 | 160 3, 4 | 250 3, 4 | 400 3, 4 | 630 3, 4 |
| AC22A / AC23A | AC22A / AC23A | AC22A / AC23A | AC22A / AC23A | AC22A / AC23A |
| 100 | 160 | 250 | 400 | 630/500 |
| 100 | 160 | 250 | 400 | 630/500 |
| 100 | 160 | 250 | 400 | 630/500 |
| 2.6 | 3.6 | 4.9 | 7.1 | 8.5 |
| 75 | 75 | 75 | 105 | 105 |
| 1800 | 2500 | 3500 | 5000 | 6000 |
| 1800 | 2500 | 3500 | 5000 | 6000 |
| 690 | 960 | 1350 | 1930 | 2320 |
| 30000 | 25000 | 20000 | 15000 | 15000 |
| AC22A / AC23A | AC22A / AC23A | AC22A / AC23A | AC22A / AC23A | AC22A / AC23A |
| 8000 | 8000 | 6500 | 4000 | 2500 |
| ■ | | ■ | | |
| ■ | | ■ | | |
| ■ | | ■ | | |
| ■ | | ■ | | |
| 105 x 161 x 86 140 x 161 x 86 1.5 to 1.8 2.0 to 2.2 | | 140 x 255 x 110 185 x 255 x 110 5.2 6.8 | | |

DE400001



Insulation accessories ▶ E-9, E-15




Connection ▶ A-16





Electrical auxiliaries ▶ A-17



Monitoring ▶ A-8



Control accessories ▶ A-19




CVS circuit breakers may be installed horizontally, vertically or flat on their back, without derating performance levels.


Fixed circuit breakers

Fixed circuit breakers are designed for standard connection using bars or cables with lugs. Bare-cable connectors are available for connection to bare copper or aluminium cables.


DB40009



DB400010



DB400011




Mounting on a backplate.

Mounting on rails.








Mounting on DIN rail (with adaptor).

DB400012



*Mounting on a Prisma
mounting plate.*

Fixed circuit breakers are designed for standard front connection using bars or cables with lugs. Cable connectors are available for bare cables. Rear connection is also possible.



Straight terminal extensions.

Right-angle terminal extensions

Spreaders.

Fixed circuit breakers are designed for standard front connection using bars or cables with lugs.

Cable connectors are available for bare cables. Rear connection is also possible.

Front connection

Bars or cables with lugs

Standard terminals

EasyPact CVS100 to 630 come with terminals comprising snap-in nuts with screws:

- EasyPact CVS100: M6 nuts and screws.
- EasyPact CVS160/250: M8 nuts and screws
- EasyPact CVS400/630: M10 nuts and screws.

These terminals may be used for:

- direct connection of insulated bars or cables with lugs
- terminal extensions.

Interphase barriers or terminal shields are recommended. They are mandatory for certain connection accessories (in which case the interphase barriers are provided).

Bars

When the switchboard configuration has not been tested, insulated bars are mandatory.

Maximum size of bars

| EasyPact CVS circuit breaker | 100/160/250 | 400/630 |
|------------------------------|-----------------------|---------|
| Without spreaders | pitch (mm) | 35 |
| | maximum bar size (mm) | 20 x 3 |
| With spreaders | pitch (mm) | 45 |
| | maximum bar size (mm) | 32 x 2 |
| | | 40 x 6 |

Crimp lugs

There are two modules of lugs, for aluminium and copper cables.

Interphase barriers or long terminal shields must be used with narrow lugs. The lugs are supplied with interphase barriers.

| EasyPact CVS circuit breaker | 100/160/250 | 400/630 |
|------------------------------|-------------------------|-------------------------------|
| Copper cables | size (mm ²) | 150, 185 |
| | crimping | hexagonal barrels or punching |
| Aluminium cables | size (mm ²) | 150, 185 |
| | crimping | hexagonal barrels |

Terminal extensions

Extensions with anti-rotation ribs can be attached to the standard terminals to provide numerous connection possibilities in little space:

- straight terminal extensions
- right-angle terminal extensions

Spreaders


Spreaders may be used to increase the pitch:

- CVS100 to 250: the 35 mm pitch can be increased to 45 mm
- CVS400/630: the 45 mm pitch can be increased to 52 or 70 mm.

Bars, cable lugs or cable connectors can be attached to the ends.

Pitch (mm) depending on the type of spreader

| EasyPact CVS circuit breaker | CVS100 to 250 | CVS100 to 630 |
|------------------------------|---------------|---------------|
| Without spreaders | 35 | 45 |
| With spreaders | 45 | 52.5 or 70 |



1-cable connector for CVS100 to 250 CVS400/630. 2-cable connector for CVS100 to 250 CVS400/630.

Bare cables

Bare-cable connectors may be used for both copper and aluminium cables.

1-cable connectors for EasyPact CVS100 to 250

The connectors snap directly on to the device terminals or are secured by clips to right-angle and straight terminal extensions as well as spreaders.

1-cable connectors for EasyPact CVS400 to 630


The connectors are screwed directly to the device terminals.

2-cable connectors for EasyPact CVS100 to 250 and 400/630

The connectors are screwed to device terminals or right-angle terminal extensions.

Maximum size of cables depending on the type of connector

| EasyPact CVS circuit breaker | 100/160 | 250 | 400 | 630 |
|------------------------------|------------------------------------|-----|-----|-----|
| Steel connectors | 1.5 to 95 mm ² | ■ | | |
| Aluminium connectors | 25 to 95 mm ² | ■ | ■ | |
| | 120 to 185 mm ² | ■ | ■ | |
| | 2 cables 50 to 120 mm ² | ■ | ■ | |
| | 2 cables 35 to 240 mm ² | | ■ | ■ |
| | 35 to 300 mm ² | ■ | ■ | ■ |



Rear connection


Device mounting on a backplate with suitable holes enables rear connection.

Bars or cables with lugs

Rear connections for bars or cables with lugs are available in two lengths. Bars may be positioned flat, on edge or at 45° angles depending on how the rear connections are positioned.

The rear connections are simply fitted to the device connection terminals. All combinations of rear connection lengths and positions are possible on a given device.

DB115583



EasyPact CVS100/160/250

Standard


All EasyPact CVS100/160/250 circuit breakers and switch-disconnectors have slots for the electrical auxiliaries listed below.

5 indication contacts (see page A-17)

- 2 ON/OFF (OF1 and OF2)
- 1 trip indication (SD)
- 1 fault-trip indication (SDE)
- 1 earth-fault indication (SDV), when the device is equipped with a Vigi module.
- 1 remote-tripping release (see page A-18)**
- either 1 MN undervoltage release
- or 1 MX shunt release.

All these auxiliaries can be installed with a rotary handle.

DB115590



EasyPact CVS400/630

Standard

All EasyPact CVS400/630 circuit breakers and switch-disconnectors have slots for the electrical auxiliaries listed below.

6 indication contacts (see page A-17)

- 3 ON/OFF (OF3)
- 1 trip indication (SD)
- 1 fault-trip indication (SDE)
- 1 earth-fault indication (SDV), when the device is equipped with a Vigi module.
- 1 remote-tripping release (see page A-18)**
- either 1 MN undervoltage release
- or 1 MX shunt release.

All these auxiliaries can be installed with a rotary handle.

The illustration shown (TMD, MA, NA and ETS 2.3 standard) indicates auxiliary possibilities depending on the type of trip unit.

One contact model provides circuit-breaker status indications (OF - SD - SDE - SDV).

These common-point changeover contacts provide remote circuit-breaker status information.

They can be used for indications, electrical locking, relaying, etc.
They comply with the IEC 60947-5 international recommendation.



Indication contacts.

DB125549

Functions

Breaker-status indications, during normal operation or after a fault

A single type of contact provides all the different indication functions:

- OF (ON/OFF) indicates the position of the circuit breaker contacts
- SD (trip indication) indicates that the circuit breaker has tripped due to:
 - an overload
 - a short-circuit
 - an earth fault (Vigi)
 - operation of a voltage release
 - operation of the "push to trip" button
 - disconnection when the device is ON.

The SD contact returns to de-energised state when the circuit breaker is reset.

- SDE (fault-trip indication) indicates that the circuit breaker has tripped due to:
 - an overload
 - a short-circuit
 - an earth fault (Vigi)

■ SDV indicates that the circuit breaker has tripped due to an earth fault. It returns de-energised state when the Vigi module is reset.

Installation

- OF, SD, SDE and SDV functions: a single type of contact provides all these different indication functions, depending on where it is inserted in the device. The contacts clip into slots behind the front cover of the circuit breaker (or the Vigi module for the SDV function).

The SDE function on a CVS100 - 630 A equipped with a magnetic, thermal-magnetic or ETS2.3 trip unit requires the SDE adaptor.

Electrical characteristics of auxiliary contacts

| Contacts | | Standard | | | | Low level | | | |
|----------------------------------|--------------|-------------------|------|------|------|------------------|------|------|------|
| Types of contacts | | All | | | | OF, SD, SDE, SDV | | | |
| Rated thermal current (A) | | 6 | | | | 5 | | | |
| Minimum load | | 100 mA at 24 V DC | | | | 1 mA at 4 V DC | | | |
| Utilisation cat. (IEC 60947-5-1) | | AC12 | AC15 | DC12 | DC14 | AC12 | AC15 | DC12 | DC14 |
| Operational current (A) | 24 V AC/DC | 6 | 6 | 6 | 1 | 5 | 3 | 5 | 1 |
| | 48 V AC/DC | 6 | 6 | 2.5 | 0.2 | 5 | 3 | 2.5 | 0.2 |
| | 110 V AC/DC | 6 | 5 | 0.6 | 0.05 | 5 | 2.5 | 0.6 | 0.05 |
| | 220/240 V AC | 6 | 4 | - | - | 5 | 2 | - | - |
| | 250 V DC | - | - | 0.3 | 0.03 | 5 | - | 0.3 | 0.03 |
| | 380/440 V AC | 6 | 2 | - | - | 5 | 1.5 | - | - |



MX or MN voltage release.




Opening conditions of the MN release.




Closing conditions of the MN release.



MN release with a time-delay unit.



Wiring diagram for emergency-off function with MN + time-delay unit.



Opening conditions of the MX release.

MN undervoltage release

- This release trips the circuit breaker when the control voltage drops below a tripping threshold
- The tripping threshold is between 0.35 and 0.7 times the rated voltage
- Circuit breaker closing is possible only if the voltage exceeds 0.85 times the rated voltage.

Characteristics

| | | | |
|-----------------------|---------|---|----------------|
| Power supply | V AC | 50/60 Hz: 24 - 48 - 100/130 - 200/240 50 Hz: 380/415 | 60 Hz: 208/277 |
| | V DC | 12 - 24 - 30 - 48 - 60 - 125 - 250 | |
| Operating threshold | Opening | 0.35 to 0.7 Un | |
| | Closing | 0.85 Un | |
| Operating range | | 0.85 to 1.1 Un | |
| Consumption (VA or W) | | Pick-up: 10 - Hold: 5 | |
| Response time (ms) | | 50 | |

Time-delay unit for an MN release

A time delay unit for the MN release eliminates the risk of nuisance tripping due to a transient voltage dip lasting ≤ 200 ms. For shorter micro-outages, a system of capacitors provides temporary supply to the MN at $U > 0.7$ to ensure no tripping. The correspondence between MN releases and time-delay units is shown below.

| Power supply | Corresponding MN release |
|--|--------------------------|
| Unit with fixed delay 200 ms | |
| 48 V AC | 48 V DC |
| 220 / 240 V AC | 250 V DC |
| Unit with adjustable delay (0.5s, 0.9s, 1.5s, 3s) | |
| 48 - 60 V AC/DC | 48 V DC |
| 100 - 130 V AC/DC | 125 V DC |
| 220 - 250 V AC/DC | 250 V DC |

MX shunt release

The MX release opens the circuit breaker via an impulse-type (≥ 20 ms) or maintained order.

Opening conditions

When the MX release is supplied, it automatically opens the circuit breaker. Opening is ensured for a voltage $U \geq 0.7 \times Un$.

Characteristics

| | | | |
|-----------------------|------|---|----------------|
| Power supply | V AC | 50/60 Hz: 24 - 48 - 100/130 - 200/240 50 Hz: 380/415 | 60 Hz: 208/277 |
| | V DC | 12 - 24 - 30 - 48 - 60 - 125 - 250 | |
| Operating range | | 0.7 to 1.1 Un | |
| Consumption (VA or W) | | Pick-up: 10 | |
| Response time (ms) | | 50 | |

Circuit breaker control by MN or MX

When the circuit breaker has been tripped by an MN or MX release, it must be reset before it can be reclosed.

MN or MX tripping takes priority over manual closing.

In the presence of a standing trip order, closing of the contacts, even temporary, is not possible.

Connection using wires up to 1.5mm^2 to integrated terminal blocks.

Note: circuit breaker opening using an MN or MX release must be reserved for safety functions. This type of tripping increases wear on the opening mechanism. Repeated use reduces the mechanical endurance of the circuit breaker by 50 %.

There are two types of rotary handle:

- direct rotary handle
- extended rotary handle.

PB106453



EasyPact CVS with a rotary handle.

PB106454



EasyPact CVS with an extended rotary handle installed at the back of a switchboard, with the keylock option and key.

PB106455



Direct rotary handle

Standard handle

Degree of protection IP40, IK07.

The direct rotary handle maintains:

- visibility of and access to trip-unit settings
- suitability for isolation
- indication of the three positions O (OFF), I (ON) and tripped
- access to the "push to trip" button.

Device locking

The rotary handle facilitates circuit-breaker locking.

■ Padlocking:

- standard situation, in the OFF position, using 1 to 3 padlocks, shackle diameter 5 to 8 mm, not supplied

Extended rotary handle

Degree of protection IP54, IK08.

The extended rotary handle makes it possible to operate circuit breakers installed at the back of switchboards, from the switchboard front.

It maintains:

- visibility of and access to trip-unit settings
- suitability for isolation
- indication of the three positions O (OFF), I (ON) and tripped.

Device and door padlocking

Padlocking locks the circuit-breaker handle and disables door opening:

- standard situation, in the OFF position, using 1 to 3 padlocks, shackle diameter 5 to 8 mm, not supplied

Parts of the extended rotary handle

- A unit that replaces the front cover of the circuit breaker (secured by screws).
- An assembly (handle and front plate) on the door that is always secured in the same position, whether the circuit breaker is installed vertically or horizontally.
- An extension shaft that must be adjusted to the distance. The min/max distance between the back of circuit breaker and door is:
 - 185...600 mm for EasyPact CVS100 to 250
 - 209...600 mm for EasyPact CVS 400/630.

Manual source-changeover systems



Additional accessory interlocks two devices with rotary handle to create a source-changeover system. Closing of one device is possible only if the second is open.

This function is compatible with direct or extended rotary handles.


Up to three padlocks can be used to lock in the OFF or ON position.

PB106456








Toggle locking using padlocks and an accessory:
Removable device Fixed device attached to the case.



Rotary-handle locking using a keylock.



Rotary-handle locking using a padlock or a keylock.



Sealing accessories.

Locks

Locking in the OFF position guarantees isolation as per IEC 60947-2. Padlocking systems can receive up to three padlocks with shackle diameters ranging from 5 to 8 mm (padlocks not supplied). Certain locking systems require an additional accessory.


| Control device | Function | Means | Required accessories |
|------------------------|---|---------|--------------------------|
| Toggle | Lock in OFF position | Padlock | Removable device |
| | Lock in OFF or ON position | Padlock | Fixed device |
| Direct rotary handle | Lock in | Padlock | - |
| | ■ OFF position | Keylock | Locking device + keylock |
| | ■ OFF or ON position ⁽¹⁾ | | |
| Extended rotary handle | Lock in | Padlock | - |
| | ■ OFF position | | |
| | ■ OFF or ON position ⁽¹⁾ with door opening prevented ⁽²⁾ | | |
| | Lock in OFF position | Padlock | UL508 control accessory |
| | ■ OFF or ON position ⁽¹⁾ | Keylock | Locking device + keylock |

⁽¹⁾ Following a simple modification of the mechanism.


⁽²⁾ Unless door locking has been voluntarily disabled.

Sealing accessories

Toggle control



Rotary handle



Access to Vigi-module settings



Types of seals

Protected operations

Protection cover for settings

- modification of settings.

Accessories and auxiliaries

Escutcheons and protection collars


Escutcheons are an optional feature mounted on the switchboard door. They increase the degree of protection to IP40, IK07. Protection collars maintain the degree of protection, whatever the position of the device (connected, disconnected).

IP40 escutcheons for fixed devices


There are three types of an escutcheon with a gasket which are screwed to the door cut-out:

- three escutcheons for all control types (toggle, handle or motor mechanism)
- a wide model for Vigi modules that can be combined with the above.

DB400041




DB400031




Escutcheon for toggle without and with access to the trip unit.

DB400032



Escutcheon for Vigi module.

Installation recommendations



Installation recommendations

Functions and characteristics

A-1

Operating conditions and temperature derating

B-2

Installation in switchboards

B-4

Power supply and weights

B-4

Safety clearances and minimum distances

B-5

Installation example

B-6

Power loss/Resistance

B-8

Dimensions and connection

C-1

Additional characteristics

D-1


Catalogue numbers

E-1


EasyPact CVS100BS

F-1


When thermal-magnetic trip units are used at ambient temperatures other than 40 °C, the Ir pick-up is modified.



Electronic trip units are not affected by variations in temperature. If the trip units are used in high-temperature environments, the ETS setting must nevertheless take into account the temperature limits of the circuit breaker.



Temperature derating curve for CVS100.



Thermal-protection curve with minimum and maximum values.

Altitude derating

Altitude does not significantly affect the characteristics of EasyPact CVS circuit breakers up to 2000 m. Above this altitude, it is necessary to take into account the decrease in the dielectric strength and cooling capacity of air.

| Altitude (m) | 2000 | 3000 | 4000 | 5000 |
|--|------|------|------|------|
| Impulse withstand voltage U_{imp} (kV) | 8 | 7 | 6 | 5.2 |
| Current ratio | 1,00 | 0,96 | 0,93 | 0,90 |
| U_i | 690 | 600 | 520 | 450 |
| U_e | 440 | 400 | 400 | 380 |

EasyPact
CVS
100-630

Vibrations

CVS devices resist electromagnetic or mechanical vibrations.

Tests are carried out in compliance with standard IEC 60068-2-6 for the levels required by merchant-marine inspection organisations (Veritas, Lloyds, etc.):

- 2 to 13.2 Hz: amplitude ± 1 mm
- 13.2 to 100 Hz: constant acceleration 0.7 g.

Excessive vibration may cause tripping, breaks in connections or damage to mechanical parts.

Degree of protection

CVS circuit breakers have been tested for degree of protection (IP) and mechanical impact protection (IK). See page A-3.

The overload protection is calibrated at 40 °C in the lab. This means that when the ambient temperature is less than or greater than 40 °C, the Ir protection pick-up is slightly modified.

To obtain the tripping time for a given temperature:

- see the tripping curves for 40 °C (see pages D-2 and D-3)
- determine tripping times corresponding to the Ir value (thermal setting on the device), corrected for the ambient temperature as indicated in the tables below.

Settings of CVS100 to 630 equipped with TM-D or TM-G* trip units as a function of the temperature

The table indicates the real Ir (A) value for a given rating and temperature.

| Rat. (A) | Temperature (°C) | 10 | 15 | 20 | 25 | 30 | 35 | 40 | 45 | 50 | 55 | 60 | 65 | 70 |
|------------|------------------|-------|-------|------|-------|-------|-----|-------|-------|-------|-------|-------|-------|----|
| 16 | 18.4 | 18 | 18 | 18 | 17 | 16.6 | 16 | 15.6 | 15.2 | 14.8 | 14.5 | 14 | 13.8 | |
| 25 | 28.8 | 28 | 27.5 | 27 | 26.3 | 25.6 | 25 | 24.5 | 24 | 23.5 | 23 | 22 | 21 | |
| 32 | 36.8 | 36 | 35.2 | 34.4 | 33.6 | 32.8 | 32 | 31.3 | 30.5 | 30 | 29.5 | 29 | 28.5 | |
| 40 | 46 | 45 | 44 | 43 | 42 | 41 | 40 | 39 | 38 | 37 | 36 | 35 | 33.5 | |
| 50 | 57.5 | 56 | 55 | 54 | 53 | 51 | 50 | 49 | 47 | 46 | 44 | 43 | 41 | |
| 63 | 73 | 72 | 70 | 68 | 67 | 65 | 63 | 61 | 59 | 57 | 55 | 53 | 50 | |
| 80 | 92 | 90 | 88 | 86 | 84 | 82 | 80 | 78 | 75.5 | 73 | 70.7 | 68 | 65 | |
| 100 | 114 | 112 | 110 | 107 | 105 | 102.5 | 100 | 97 | 95 | 92.0 | 89 | 86 | 83 | |
| 125 | 144 | 141 | 138 | 134 | 131 | 128 | 125 | 122 | 119 | 116 | 113 | 109 | 106 | |
| 160 | 184 | 180 | 176 | 172 | 168 | 164 | 160 | 156 | 152 | 148 | 144 | 140 | 136 | |
| 200 | 230 | 225 | 220 | 215 | 210 | 205 | 200 | 195 | 190 | 185 | 180 | 175 | 170 | |
| 250 | 288 | 281 | 277 | 269 | 263 | 256 | 250 | 244 | 238 | 231 | 225 | 219 | 213 | |
| 320 | 365 | 358 | 350.5 | 343 | 335.6 | 328 | 320 | 312 | 303.6 | 295 | 286 | 277 | 267.7 | |
| 400 | 456.6 | 447.7 | 438.6 | 429 | 419.7 | 410 | 400 | 390 | 379.3 | 368.5 | 357.3 | 345.8 | 334 | |
| 500 | 558.6 | 549 | 539.7 | 530 | 520.3 | 510.2 | 500 | 489.6 | 479 | 468 | 457 | 445.4 | 433.6 | |
| 600 | 672 | 660.5 | 649 | 637 | 625 | 612.6 | 600 | 587 | 574 | 560.6 | 547 | 532.7 | 518 | |

* For TM-G, the rating is from 80A to 250A.

CVS400 and 630 (equipped with ETS2.3 electronic trip unit)


The table below indicates the maximum long-time (LT) protection setting I_r (A) depending on the ambient temperature.

| Type of device | Rating (A) | Temperature (°C) | | | | | | |
|----------------|------------|------------------|-----|-----|-----|-----|-----|-----|
| | | 40 | 45 | 50 | 55 | 60 | 65 | 70 |
| CVS400 | | | | | | | | |
| Fixed | 400 | 400 | 400 | 400 | 390 | 380 | 370 | 360 |
| CVS630 | | | | | | | | |
| Fixed | 630 | 630 | 615 | 600 | 585 | 570 | 550 | 535 |

Additional derating coefficient for an add-on module

For fixed circuit breakers equipped with a Vigi module, the coefficients in the table below must be applied.

| Circuit breaker | Trip unit | Coefficient |
|-----------------|-----------|-------------|
| CVS400 | TMD320 | 0.98 |
| | TMD400 | 0.94 |
| | ETS2.3 | 0.97 |
| CVS630 | TMD500 | 0.9 |
| | TMD600 | 0.89 |
| | ETS2.3 | 0.9 |



Power supply from the top or bottom

CVS circuit breakers can be supplied from either the top or the bottom, even when equipped with a Vigi earth-leakage protection module, without any reduction in performance. This capability facilitates connection when installed in a switchboard. All connection and insulation accessories can be used on circuit breakers supplied either from the top or bottom.

Weight

The table below presents the weights (in kg) of the circuit breakers and Vigi module.

| Type of device | Circuit breakers | | | Vigi module |
|----------------|------------------|---------------|--------------|-------------|
| | CVS with TM-D | CVS with TM-G | CVS with ETS | |
| CVS100 | 3P 3D | 1.64 | - | 0.87 |
| | 4P 4D | 2.01 | - | 1.13 |
| | 4P 3D | 2.01 | - | 1.13 |
| CVS160 | 3P 3D | 1.60 | 1.60 | 0.87 |
| | 4P 4D | 2.08 | - | 1.13 |
| | 4P 3D | 2.08 | 2.08 | 1.13 |
| CVS250 | 3P 3D | 1.79 | 1.79 | 0.87 |
| | 4P 4D | 2.39 | - | 1.13 |
| | 4P 3D | 2.39 | 2.39 | 1.13 |
| CVS400 | 3P 3D | 4.37 | - | 4.71 |
| | 4P 4D | 5.83 | - | 6.32 |
| | 4P 3D | 5.83 | - | 6.32 |
| CVS630 | 3P 3D | 4.80 | - | 5.24 |
| | 4P 4D | 6.40 | - | 7.14 |
| | 4P 3D | 6.40 | - | 7.14 |

General rules

When installing a circuit breaker, minimum distances (safety clearances) must be maintained between the device and panels, bars and other protection devices installed nearby. These distances, which depend on the ultimate breaking capacity, are defined by tests carried out in accordance with standard IEC 60947-2.

If installation conformity is not checked by type tests, it is also necessary to:







- use insulated bars for circuit-breaker connections
- segregate the busbars using insulating screens.

For CVS100 to 630 devices, terminal shields and interphase barriers are recommended and may be mandatory depending on the operating voltage of the device and type of installation (fixed, withdrawable, etc.).

Power connections

The table below indicates the rules to be respected for CVS100 to 630 devices to ensure the insulation of live parts for fixed devices.


CVS100 to 630: rules to be respected to ensure the insulation of live parts

| Type of connection | Fixed, front connection | Fixed, rear connection |
|--|---|--|
| |  DB400039 |  DB400040 |
| Possible, recommended or mandatory accessories: With: | No insulating accessory  DB115098 | Interphase barriers  DB115080 |
| | Long terminal shields ⁽¹⁾ | Short terminal shields  DB115056 |
| operating voltage | type of conductor | |
| ≤ 440 V | Insulated bars  | Possible Possible Possible Recommended |
| | Extension terminals Cables + crimp lugs  | No Mandatory (supplied) Possible (instead of ph. barriers) Recommended |
| | Bare cables + connectors  | Possible for CVS100 to 250 No Mandatory (supplied) Possible (instead of ph. barriers) Recommended |


⁽¹⁾ Long terminal shields provide a degree of protection of IP40 (ingress) and IK07 (mechanical impact).

Safety clearance

Minimum distance between two adjacent circuit breakers




Minimum distance between circuit breaker and front or rear panels



Bare or painted sheet metal

Note: if $F < 8 \text{ mm}$: an insulating screen or long terminal shield is mandatory.

Minimum distance between circuit breaker and top, bottom or side panels




Devices without accessories.

Devices with interphase barriers or long terminal shields.

Minimum safety clearances for CVS100 to 630

| Dimensions (mm) circuit breaker | Insulation, insulated bars or painted sheet metal | | | Bare sheet metal | | | |
|------------------------------------|--|----|----|------------------|----|----|----|
| | C1 | D1 | D2 | C1 | D1 | D2 | A1 |
| CVS100-250 U ≤ 440V | 0 | 30 | 30 | 5 | 35 | 35 | 0 |
| CVS400-630 U ≤ 440V | 0 | 30 | 30 | 5 | 60 | 60 | 0 |



Live busbars.


Clearances with respect to live bare busbars

Minimum clearances for CVS100 to 630

| Operating voltage | Clearances with respect to live bare busbars | | | |
|-------------------|--|-----|-----------------|-----|
| | spacing ≤ 60 mm | | spacing > 60 mm | |
| | F1 | F2 | F1 | F2 |
| U < 440 V | 350 | 350 | 80 | 80 |
| U = 440 V | 350 | 350 | 120 | 120 |

These clearances can be reduced for special installations as long as the configuration is checked by tests.

EasyPact CVS thermal power loss values are used to calculate total temperature rise in the switchboard in which the circuit breakers are installed.



With a Vigi module, the deviation of the N and L3 bars required to pass through the toroid results in higher power losses compared to those of the L1 and L2 bars.

The values indicated in the tables below are typical values for a device at full rated load and 50/60 Hz.

Power loss per pole (P/pole) in Watts (W)

The value indicated is the power loss at I_{N_r} , 50/60 Hz, for a three-pole or four-pole circuit breaker. Measurement and calculation of power loss are carried out in compliance with the recommendations of Annex G of standard IEC 60947-2.

Resistance per pole (R/pole) in milliohms ($m\Omega$)

The value of the resistance per pole is provided as a general indication for a new device.

The value of the contact resistance must be determined on the basis of the measured voltage drop, in accordance with the manufacturer's test procedure (ABT instruction document no. 1 - BEE - 02.2 -A).

Note: this measurement is not sufficient to determine the quality of the contacts, i.e. the capacity of the circuit breaker to carry its rated current.

Additional power loss

Additional power loss is equal to the sum of the power dissipated by the following:

- Vigi module: note that the deviation of the N and L3 bars required to pass through the toroid results in higher power losses compared to those of the L1 and L2 bars (diagram opposite). When calculating total power loss, use L1, L2, L3 for a 3P device and N, L1, L2, L3 for a 4P device
- disconnecting contacts (plug-in and withdrawable devices)
- ammeter module
- transformer module.

Calculation of total power loss

Total power loss at full rated load and 50/60 Hz is equal to the sum of the device and additional power losses per pole multiplied by the number of poles (2, 3 or 4).

If a Vigi module is installed, it is necessary to differentiate between N and L3 on one hand and L1 and L2 on the other.

EasyPact CVS100 to 630 equipped with TM-D trip units

| Type of device 3/4 poles | Fixed device | | | Additional power/pole | |
|-----------------------------|--------------------|--------|--------|-----------------------|-----------------|
| | Rat. (A) | R/pole | P/pole | Vigi (N,L3) | Vigi (L1,L2) |
| CVS100 | 16 | 11.91 | 3.05 | 0 | 0 |
| | 25 | 6.91 | 4.32 | 0 | 0 |
| | 32 | 4.43 | 4.54 | 0.06 | 0.03 |
| | 40 | 4.125 | 6.60 | 0.1 | 0.05 |
| | 50 | 3.30 | 8.25 | 0.15 | 0.08 |
| | 63 | 1.92 | 7.62 | 0.3 | 0.15 |
| | 80 | 1.86 | 11.90 | 0.4 | 0.2 |
| | 100 | 1.37 | 13.70 | 0.7 | 0.35 |
| CVS160 | 100 | 0.77 | 7.70 | 0.7 | 0.35 |
| | 125 | 0.69 | 10.78 | 1.1 | 0.55 |
| | 160 | 0.55 | 14.08 | 1.8 | 0.9 |
| | 160 | 0.46 | 11.78 | 1.8 | 0.9 |
| CVS250 | 200 | 0.39 | 15.60 | 2.8 | 1.4 |
| | 250 | 0.3 | 18.75 | 4.4 | 2.2 |
| | 320 | 0.24 | 24.00 | 2.05 | 1.03 |
| CVS400 | 400 ⁽¹⁾ | 0.19 | 30.00 | 2.86 | 1.43 |
| | 500 ⁽²⁾ | 0.17 | 40.80 | 4.08 | 2.04 |
| | 600 ⁽³⁾ | 0.15 | 53.80 | 5.7 | 2.85 |

(1) The power loss value for Vigi module is given for 378A

(2) The power loss value for Vigi module is given for 451A

(3) The power loss value for Vigi module is given for 534A

EasyPact CVS100 to 630 equipped with MA trip units

| Type of device 3/4 poles | Fixed device | | | Additional power/pole | |
|-----------------------------|--------------|--------|--------|-----------------------|-----------------|
| | Rat. (A) | R/pole | P/pole | Vigi (N,L3) | Vigi (L1,L2) |
| CVS100 | 2.5 | 148.91 | 0.93 | 0 | 0 |
| | 6.3 | 99.51 | 3.95 | 0 | 0 |
| | 12.5 | 4.54 | 0.71 | 0 | 0 |
| | 25 | 2.15 | 1.34 | 0 | 0 |
| | 50 | 1.16 | 2.90 | 0.2 | 0.1 |
| | 100 | 0.52 | 5.20 | 0.7 | 0.35 |
| CVS160 | 150 | 0.38 | 8.55 | 1.35 | 0.68 |
| CVS250 | 220 | 0.3 | 14.52 | 2.9 | 1.45 |
| CVS400 | 320 | 0.15 | 15.40 | 3.2 | 1.6 |
| CVS630 | 500 | 0.13 | 32.20 | 13.99 | 7 |

The values indicated in the table below are typical values for a device at full rated load and 50/60 Hz. The definitions and information are the same as that for circuit breakers equipped with thermal-magnetic trip units.

CVS400 to 630 equipped with electronic trip units

| Type of device 3/4 poles | Fixed device | | | Additional power/pole | |
|-----------------------------|--------------------|--------|--------|-----------------------|-----------------|
| | Rat. (A) | R/pole | P/pole | Vigi (N,L3) | Vigi (L1,L2) |
| CVS400 | 400 | 0.15 | 24.00 | 3.2 | 1.6 |
| CVS630 ⁽⁴⁾ | 630 ⁽⁴⁾ | 0.12 | 47.63 | 6.5 | 3.25 |

(4) The power loss value for Vigi module is given for 570A

Dimensions and connection





Dimensions and connection



| | |
|--------------------------------------|-----|
| <i>Functions and characteristics</i> | A-1 |
| <i>Installation recommendations</i> | B-1 |

| | |
|---|-------------|
| Dimensions and mounting | C-2 |
| EasyPact CVS100 to 630 | C-2 |
| Vigi CVS100 to 630 | C-3 |
| Direct rotary handle for EasyPact and Vigi CVS100 to 630 | C-4 |
| Extended rotary handle for EasyPact CVS100 to 630 | C-5 |
| Front-panel accessories | C-6 |
| EasyPact CVS100 to 630 | C-6 |
| Front-panel cutouts | C-7 |
| EasyPact CVS100 to 630 | C-7 |
| Vigi CVS100 to 630 | C-8 |
| Direct rotary handle for EasyPact and Vigi CVS100 to 630 | C-9 |
| Power connections | C-11 |
| EasyPact and Vigi CVS100 to 630 | C-11 |
| Connection of insulated bars or cables with lugs to EasyPact and Vigi CVS100 to 630 | C-14 |
| Connection of bare cables to EasyPact and Vigi CVS100 to 630 | C-15 |

| | |
|-----------------------------------|-----|
| <i>Additional characteristics</i> | D-1 |
| <i>Catalogue numbers</i> | E-1 |
| <i>EasyPact CVS100BS</i> | F-1 |












(1) The ØT holes are required for rear connection only.



Dimensions and connection

Dimensions and mounting Vigi CVS100 to 630


| Dimensions | 3/4P | 3/4P | | | | | | | | | | | | | | | |
|---|---|--|-------|-------|-------|-------|-----|-------|------|-------|------|-----|------|------|------|--------------------|------|
|  |  |  | | | | | | | | | | | | | | | |
| Mounting | CVS100 to 250 | CVS400/630 | | | | | | | | | | | | | | | |
| On backplate | 3P | 3P | | | | | | | | | | | | | | | |
|  |  |  | | | | | | | | | | | | | | | |
| (1) The ØT holes are required for rear connection only. | | | | | | | | | | | | | | | | | |
| On rails | 3P | 3P | | | | | | | | | | | | | | | |
|  |  |  | | | | | | | | | | | | | | | |
| Type | A | A1 | A2 | A3 | A4 | A5 | A6 | A7 | A8 | A9 | B | B1 | B2 | C1 | C2 | C3 | E1 |
| CVS100/160/250 | 80.5 | 161 | 94 | 145 | 178.5 | 155.5 | 236 | 169 | 220 | 253.5 | 52.5 | 105 | 140 | 81 | 86 | 111 ⁽²⁾ | 62.5 |
| CVS400/630 | 127.5 | 255 | 142.5 | 200 | 237 | 227.5 | 355 | 242.5 | 300 | 337 | 70 | 140 | 185 | 95.5 | 110 | 168 | 100 |
| Type | E2 | E3 | E4 | E5 | E6 | E7 | E8 | F1 | F2 | F3 | G1 | G2 | G3 | G4 | G5 | ØT | U |
| CVS100/160/250 | 125 | 70 | 140 | 137.5 | 200 | 145 | 215 | 35 | 17.5 | 70 | 95 | 75 | 13.5 | 23 | 17.5 | 24 | ≤32 |
| CVS400/630 | 200 | 113.5 | 227 | 200 | 300 | 213.5 | 327 | 45 | 22.5 | 90 | - | - | - | - | - | 32 | ≤35 |

(2) C3=126mm for EasyPact CVS250/B.

Dimensions and connection

Dimensions and mounting

Direct rotary handle for EasyPact
and Vigi CVS100 to 630



| Type | A14 | A15 | A18 | B8 | B9 | B10 | C7 | C8 | C9 |
|----------------|------|-----|------|------|-----|------|-----|-----|-----|
| CVS100/160/250 | 27.5 | 73 | 9 | 45.5 | 91 | 9.25 | 121 | 155 | 164 |
| CVS400/630 | 40 | 123 | 24.6 | 61.5 | 123 | 5 | 145 | 179 | 188 |

Dimensions and connection



Dimensions and mounting

Extended rotary handle for EasyPact CVS100 to 630

Dimensions

Fixed circuit breakers



DB400171



Cutout for shaft (mm)

| Type | R1 |
|----------------|----------------------|
| CVS100/160/250 | min. 171 max. 600 |
| CVS400/630 | min. 195 max. 600 |





Dimensions and front-panel cutout







| Type | A18 | B10 |
|----------------|------|------|
| CVS100/160/250 | 9 | 9.25 |
| CVS400/630 | 24.6 | 5 |

IP40 front-panel escutcheons





For toggle





For rotary handle or module and protection collar









For Vigi












| Type | A1 | A2 | A3 | B1 | M2 | M3 |
|----------------|-----|-----|-----|-----|-----|-----|
| CVS100/160/250 | 91 | 114 | 101 | 157 | 115 | 102 |
| CVS400/630 | 123 | 164 | 151 | 189 | 155 | 142 |





| Type | P3 | P4 | R | R1 |
|----------------|-----|-----|------|----|
| CVS100/160/250 | 88 | 83 | 14.5 | 29 |
| CVS400/630 | 112 | 107 | 31.5 | 63 |

| Bare sheet metal | CVS100 to 250 | CVS400/630 |
|--|--|--|
| For toggle | | |
|  |  |  |
| For toggle with access to trip unit | | |
|  |  |  |

| Fixed circuit breakers | CVS100 to 250 | CVS400/630 |
|---|---|---|
| Bare sheet metal | | |
|  |  |  |
| Bare sheet metal with access to the trip unit | | |
|  |  |  |
| With IP30 front-panel escutcheon | | |
|  |  |  |


Fixed circuit breakers (cont.)

With IP30 front-panel escutcheon with access to the trip unit







CVS100 to 250

CVS400/630





With IP40 front-panel escutcheon



| Type | P10 | P11 | P12 |
|----------------|-----|-----|-----|
| CVS100/160/250 | 89 | 90 | 123 |
| CVS400/630 | 112 | 113 | 147 |




Connection locations



| Type | A1 | A2 | B1 | C1 | C2 |
|------------|-------|-----|----|------|------|
| CVS100/160 | 70 | 140 | 35 | 19.5 | 19.5 |
| CVS250 | 70 | 140 | 35 | 21.5 | 19.5 |
| CVS400/630 | 113.5 | 227 | 45 | 26 | 26 |




| Type | A1 | A3 | B1 | C1 | C2 |
|-------------------|-------|-----|----|------|------|
| CVS100/160 + Vigi | 70 | 215 | 35 | 19.5 | 21.5 |
| CVS250 + Vigi | 70 | 215 | 35 | 21.5 | 21.5 |
| CVS400/630 + Vigi | 113.5 | 327 | 45 | 26 | 26 |

Front connection without accessories



Connection with accessories


Long and short rear connectors



Connection with accessories (cont.)


Bare-cable connectors

DB400138




CVS100 to 250


DB115451



DB115452




DB400139




CVS400/630

DB115454




DB115455




Distribution connectors (for CVS100 to 250 only)

DB115456




DB115457



(a) Vigi module
or CVS250.


Right-angle terminal extensions (upstream only)

DB400140



CVS100 to 250


DB115459



(b) CVS250.


CVS400/630

DB115460




Straight terminal extensions (for CVS100 to 250 only)

DB400141




DB115462




Connection with accessories (cont.)


Spreaders




3P




4P



CVS100 to 250



CVS400/630





| Type | C3 | C4 | E1 | E2 | E3 | F1 | F2 |
|------------|------|----|-----|------|-------|-------|----|
| CVS100/160 | 23.5 | - | 114 | 45 | 159 | 100 | 11 |
| CVS250 | 25.5 | - | 114 | 45 | 159 | 100 | 11 |
| CVS400/630 | - | 44 | 135 | 52.5 | 187.5 | 152.5 | 15 |
| | | | 170 | 70 | 240 | 166 | 15 |

Dimensions and connection


Power connections

Connection of insulated bars or cables with lugs to EasyPact and Vigi CVS100 to 630




Accessories for CVS100 to 250

Straight terminal extensions



Tinned copper


Spreaders: separate parts



Tinned copper


Accessories for CVS400 and 630

Spreaders made up of separate parts for 52.5 and 70 mm pitch



Accessories for CVS100 to 630

Right-angle terminal extensions



Tinned copper
To be mounted on upstream side.

Direct connection to CVS100 to 630

| Dimensions | CVS100 | CVS160/250 | CVS400/630 |
|------------------------|------------------|----------------|----------------|
| Bars | L (mm) ≤ 25 | L (mm) ≤ 25 | d + 10 ≤ 32 |
| | I (mm) d + 10 | | d + 15 |
| | d (mm) ≤ 10 | | ≤ 15 |
| | e (mm) ≤ 6 | | 3 ≤ e ≤ 10 |
| | Ø (mm) 6.5 | | 10.5 |
| Lugs | L (mm) ≤ 25 | L (mm) ≤ 25 | Ø (mm) 6.5 |
| | Ø (mm) 8.5 | | 10.5 |
| Torque (Nm) (1) | 10 | 15 | 50 |
| Torque (Nm) (2) | 5/5 | 5/5 | 20/11 |

(1) Tightening torque on the circuit breaker for lugs or bars.

(2) Tightening torque on fixed devices for rear connectors.

Connection with accessories to CVS100 to 250 (IEC 228)

| Pole pitch | Without spreaders | | With spreaders or terminal extensions | |
|------------------------|-----------------------|-----------------------|---------------------------------------|----------------|
| | 35 mm | 45 mm | CVS100 | CVS160/250 |
| Bars | L (mm) ≤ 25 | L (mm) 20 ≤ I ≤ 25 | I (mm) ≤ 25 | d (mm) ≤ 10 |
| | I (mm) 20 ≤ I ≤ 25 | | 20 ≤ I ≤ 25 | e (mm) ≤ 6 |
| | d (mm) ≤ 10 | | | Ø (mm) 6.5 |
| | e (mm) ≤ 6 | | | 8.5 |
| | Ø (mm) 6.5 | | | 10.5 |
| Lugs | L (mm) ≤ 25 | L (mm) ≤ 25 | Ø (mm) 6.5 | Ø (mm) 8.5 |
| | Ø (mm) 8.5 | | | 10.5 |
| Torque (Nm) (1) | 10 | | | 15 |

(1) Tightening torque on the circuit breaker for spreaders or terminal extensions.


Spreaders and straight, right-angle, 45°, double-L and edgewise terminal extensions are supplied with flexible interphase barriers.

Connection with accessories to CVS400 and 630 (IEC 228)

| Pole pitch | Without spreaders | With spreaders | With terminal extensions |
|------------------------|----------------------|-----------------------|--------------------------|
| | 45 mm | 52.5 or 70 mm | |
| Bars | L (mm) ≤ 40 | L (mm) d + 15 | L (mm) ≤ 32 |
| | I (mm) ≤ 20 | I (mm) 30 ≤ I ≤ 34 | I (mm) ≤ 15 |
| | d (mm) ≤ 20 | | 3 ≤ e ≤ 10 |
| | e (mm) 3 ≤ e ≤ 10 | | 3 ≤ e ≤ 10 |
| | Ø (mm) 12.5 | | 10.5 |
| Lugs | L (mm) ≤ 40 | L (mm) ≤ 32 | Ø (mm) 12.5 |
| | Ø (mm) 12.5 | | 10.5 |
| Torque (Nm) (1) | 50 | | 50 |


(1) Tightening torque on the circuit breaker for spreaders or terminal extensions.

Spreaders and right-angle, 45° and edgewise terminal extensions are supplied with flexible interphase barriers.




Mounting detail: 2 cables with lugs.

DB400149



Connection for CVS100 to 250




1-cable connector 2-cable connector

| | 1-cable connector | Steel ≤ 160 A | Aluminium ≤ 250 A | |
|----------|----------------------------|--------------------------|----------------------|----------|
| DB115963 | L (mm) | 25 | 25 | |
| | S (mm ²) Cu/Al | 1.5 to 95 ⁽¹⁾ | 25 to 50 | 70 to 95 |
| | Torque (Nm) | 12 | 20 | 26 |
| | 2-cable connector | | | |
| | L (mm) | 25 or 50 | | |
| | S (mm ²) Cu/Al | 2 x 50 to 2 x 120 | | |
| | Torque (Nm) | 22 | | |

⁽¹⁾ For flexible cables from 1.5 to 4 mm², connection with crimped or self-crimping ferrules.

Connection to CVS400 and 630



Conductor materials and electrodynamic stresses

EasyPact CVS circuit breakers can be connected indifferently with bare-copper, tinned-copper and tinned-aluminium conductors (flexible or rigid bars, cables). In the event of a short-circuit, thermal and electrodynamic stresses will be exerted on the conductors. They must therefore be correctly sized and held in place by supports.

Electrical connection points on switchgear devices (switch-disconnectors, contactors, circuit breakers, etc.) should not be used for mechanical support. Any partition between upstream and downstream connections of the device must be made of non-magnetic material.

Additional characteristics



Additional characteristics


| | |
|--------------------------------------|-----|
| <i>Functions and characteristics</i> | A-1 |
| <i>Installation recommendations</i> | B-1 |
| <i>Dimensions and connection</i> | C-1 |

| | |
|---|------|
| Tripping curves | D-2 |
| EasyPact CVS100 to 630 Protection of distribution systems | D-2 |
| EasyPact CVS100 to 250 Protection of generator systems | D-6 |
| EasyPact CVS100 to 250 Motor protection | D-8 |
| Current and energy limiting curves | D-9 |
| Selectivity | D-11 |
| Cascading | D-20 |
| Switch disconnector coordination | D-22 |


| | |
|--------------------------|-----|
| <i>Catalogue numbers</i> | E-1 |
| EasyPact CVS100BS | F-1 |

TM magnetic trip units


TM16D




TM25D



TM32D




TM40D




Reflex tripping.

TM magnetic trip units

TM50D




TM63D




Reflex tripping.

Reflex tripping.

TM80D/100D



TM125D/160D




Additional characteristics

Tripping curves


EasyPact CVS400 to 630

Protection of distribution systems


TM200D/250D




TM320D/400D



TM500D




TM600D




ETS2.3 electronic trip units

ETS2.3 400 A



ETS2.3 630 A



Reflex tripping.

Reflex tripping.


Tripping curves

EasyPact CVS100 to 250


Protection of generator systems

TM magnetic trip units

TM80G




TM100G




Reflex tripping.

TM125G




Reflex tripping.

TM160G



Reflex tripping.

TM200G and TM250G


Tripping curves

EasyPact CVS100 to 250

Motor protection

MA magnetic trip units



MA2.5... MA100




Reflex tripping.

MA150 and MA220

MA150 and MA220


**MA320****MA500**

Reflex tripping.



Reflex tripping.

The limiting capacity of a circuit breaker is its aptitude to let through a current, during a short-circuit, that is less than the prospective short-circuit current.



The exceptional limiting capacity of the EasyPact CVS range is due to the rotating double-break technique (very rapid natural repulsion of contacts and the appearance of two arc voltages in-series with a very steep wavefront).

I_{cs} = 100 % I_{cu}

The exceptional limiting capacity of the EasyPact CVS range greatly reduces the forces created by fault currents in devices.

The result is a major increase in breaking performance.

In particular, the service breaking capacity I_{cs} is equal to 100 % of I_{cu}.

The I_{cs} value, defined by IEC standard 60947-2, is guaranteed by tests comprising the following steps:

- break three times consecutively a fault current equal to 100% of I_{cu}
- check that the device continues to function normally, that is:
 - it conducts the rated current without abnormal temperature rise
 - protection functions perform within the limits specified by the standard
 - suitability for isolation is not impaired.

Longer service life of electrical installations

Current-limiting circuit breakers greatly reduce the negative effects of short-circuits on installations.

Thermal effects

Less temperature rise in conductors, therefore longer service life for cables.

Mechanical effects

Reduced electrodynamic forces, therefore less risk of electrical contacts or busbars being deformed or broken.

Electromagnetic effects

Fewer disturbances for measuring devices located near electrical circuits.

Current and energy limiting curves

The limiting capacity of a circuit breaker is expressed by two curves which are a function of the prospective short-circuit current (the current which would flow if no protection devices were installed):


- the actual peak current (limited current)
- thermal stress (A²s), i.e. the energy dissipated by the short-circuit in a conductor with a resistance of 1 Ω.

Maximum permissible cable stresses


The table below indicates the maximum permissible thermal stresses for cables depending on their insulation, conductor (Cu or Al) and their cross-sectional area (CSA). CSA values are given in mm² and thermal stresses in A²s.

| CSA | 1.5 mm ² | 2.5 mm ² | 4 mm ² | 6 mm ² | 10 mm ² |
|------------|---------------------|----------------------|----------------------|----------------------|----------------------|
| PVC | Cu | 2.97x10 ⁴ | 8.26x10 ⁴ | 2.12x10 ⁵ | 4.76x10 ⁵ |
| | Al | | | | 5.41x10 ⁵ |
| PRC | Cu | 4.10x10 ⁴ | 1.39x10 ⁵ | 2.92x10 ⁵ | 6.56x10 ⁵ |
| | Al | | | | 7.52x10 ⁵ |
| CSA | 16 mm ² | 25 mm ² | 35 mm ² | 50 mm ² | |
| PVC | Cu | 3.4x10 ⁶ | 8.26x10 ⁶ | 1.62x10 ⁷ | 3.31x10 ⁷ |
| | Al | 1.39x10 ⁶ | 3.38x10 ⁶ | 6.64x10 ⁶ | 1.35x10 ⁷ |
| PRC | Cu | 4.69x10 ⁶ | 1.39x10 ⁷ | 2.23x10 ⁷ | 4.56x10 ⁷ |
| | Al | 1.93x10 ⁶ | 4.70x10 ⁶ | 9.23x10 ⁶ | 1.88x10 ⁷ |

Current-limiting curves



Energy-limiting curves



Selectivity

How to use the selectivity tables

Combinaisons providing full selectivity are indicated by the symbol T
(up to downstream breaker Icu)

If selectivity is partial, the table indicates the maximum fault current value (kA)
until which selectivity is ensured.

Requisite conditions

The values indicated in the tables are valid for operational rated voltage 380V 400V
415V 50-60Hz.

Following ratios shall be respected in order to avoid overlapping of tripping
curves.

| Upstream | Downstream | Ir up / ir down | Im up / Im down |
|------------|------------|-----------------|-----------------|
| TM | TM | 1.6 | 2 |
| | MA + O/L | 3 | 2 |
| ETU | TM | 1.6 | 2 |
| | ETU | 1.3 (1) | 1.5 |
| | MA + O/L | 3 | 2 |
| Micrologic | TM | 1.6 | 2 |
| | ETU | 1.3 (1) | 1.5 |
| | MA + O/L | 3 | 2 |

When Magnetic threshold is adjustable, table are based on maximum setting
Im (= 10xIr typically)

When tr is adjustable tr upstream > tr downstream

When tsd is adjustable tsd upstream > tsd downstream

Ue ≤ 415 Vac

| Upstream Trip Unit | | EasyPact CVS100 B/F/N TM•D | | | | | CVS160 B/F/N TM•D | | | | | | CVS250 B/F/N TM•D | | |
|------------------------|--------------|-------------------------------|-----------|-----------|-----------|-----------|----------------------|-----------|------------|------------|-------------|-------------|----------------------|-------------|-------------|
| Downstream | Rating Im | 16 190 | 25 300 | 32 400 | 40 500 | 50 500 | 63 500 | 80 640 | 100 800 | 100 800 | 125 1250 | 160 1250 | 160 1250 | 200 1000 | 250 1250 |
| Selectivity Limit (kA) | | | | | | | | | | | | | | | |
| iK60N | ≤ 10 | 0.19 | 0.3 | 0.4 | 0.9 | 0.9 | 0.9 | 0.63 | 0.8 | 0.8 | 2.5 | 5 | 5 | T | T |
| B-C Curves | 16 | | 0.3 | 0.4 | 0.5 | 0.5 | 0.5 | 0.63 | 0.8 | 0.8 | 3 | 3 | 3 | T | T |
| 1P 230V | 20 | | | 0.4 | 0.5 | 0.5 | 0.5 | 0.63 | 0.8 | 0.8 | 2.5 | 2.5 | 2.5 | T | T |
| 2,3,4P 400V | 25 | | | | 0.5 | 0.5 | 0.5 | 0.63 | 0.8 | 0.8 | 2 | 2 | 2 | T | T |
| | 32 | | | | | 0.5 | 0.5 | 0.63 | 0.8 | 0.8 | 1.5 | 1.5 | 1.5 | 5 | T |
| | 40 | | | | | | 0.5 | 0.63 | 0.8 | 0.8 | 1.5 | 1.5 | 1.5 | 4.5 | T |
| | 50 | | | | | | | 0.63 | 0.8 | 0.8 | 1.5 | 1.5 | 1.5 | 4 | T |
| | 63 | | | | | | | | 0.8 | 0.8 | 1.5 | 1.5 | 1.5 | 3 | 5 |

4 Selectivity limit = 4kA

T Total selectivity, up to the breaking capacity of the downstream circuit breaker.

No Selectivity

Nota: respect the basic rules of selectivity for overload and short-circuit.

See Introduction

$U_e \leq 415 \text{ Vac}$

| Upstream Trip Unit | | EasyPact CVS100BS | | | | | | | | |
|------------------------|--------------|-------------------|-----------|-----------|-----------|-----------|-----------|-----------|------------|-------------|
| Downstream | Rating Im | 16 300 | 20 300 | 25 300 | 32 300 | 40 500 | 50 500 | 63 750 | 80 1000 | 100 1000 |
| Selectivity Limit (kA) | | | | | | | | | | |
| iK60N | ≤ 10 | 0.3 | 0.3 | 0.3 | 0.3 | 0.5 | 0.5 | 0.75 | 1 | 1 |
| B-C Curves | 16 | | | 0.3 | 0.3 | 0.5 | 0.5 | 0.75 | 1 | 1 |
| 1P 230V | 20 | | | | 0.3 | 0.5 | 0.5 | 0.75 | 1 | 1 |
| 2,3,4P 400V | 25 | | | | | 0.5 | 0.5 | 0.75 | 1 | 1 |
| | 32 | | | | | | 0.5 | 0.75 | 1 | 1 |
| | 40 | | | | | | | 0.75 | 1 | 1 |
| | 50 | | | | | | | | 1 | 1 |
| | 63 | | | | | | | | | 1 |

 Selectivity limit = 4kA

 Total selectivity, up to the breaking capacity of the downstream circuit breaker.

 No Selectivity

Nota: respect the basic rules of selectivity for overload and short-circuit. See Introduction

Ue ≤ 415 Vac

| Upstream Trip Unit | | EasyPact CVS100 B/F/N TM•D | | | | | CVS160 B/F/N TM•D | | | | | CVS250 B/F/N TM•D | | | |
|-------------------------------|--------------|-------------------------------|-----------|-----------|-----------|-----------|----------------------|-----------|------------|------------|-------------|----------------------|-------------|-------------|-------------|
| Downstream | Rating Im | 16 190 | 25 300 | 32 400 | 40 500 | 50 500 | 63 500 | 80 640 | 100 800 | 100 800 | 125 1250 | 160 1250 | 160 1250 | 200 1000 | 250 1250 |
| Selectivity Limit (kA) | | | | | | | | | | | | | | | |
| CVS100 BS | 16 | | 0.3 | 0.4 | 0.5 | 0.5 | 0.5 | 0.63 | 0.8 | 0.8 | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 |
| TM•D | 20 | | | 0.4 | 0.5 | 0.5 | 0.5 | 0.63 | 0.8 | 0.8 | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 |
| | 25 | | | | 0.5 | 0.5 | 0.5 | 0.63 | 0.8 | 0.8 | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 |
| | 32 | | | | | 0.5 | 0.5 | 0.63 | 0.8 | 0.8 | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 |
| | 40 | | | | | | 0.5 | 0.63 | 0.8 | 0.8 | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 |
| | 50 | | | | | | | 0.63 | 0.8 | 0.8 | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 |
| | 63 | | | | | | | | 0.8 | 0.8 | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 |
| | 80 | | | | | | | | | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 | |
| | 100 | | | | | | | | | | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 | |
| CVS100 B/F/N | 16 | | 0.3 | 0.4 | 0.5 | 0.5 | 0.5 | 0.63 | 0.8 | 0.8 | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 |
| TM•D | 25 | | | 0.5 | 0.5 | 0.5 | 0.5 | 0.63 | 0.8 | 0.8 | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 |
| | 32 | | | | 0.5 | 0.5 | 0.5 | 0.63 | 0.8 | 0.8 | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 |
| | 40 | | | | | 0.5 | 0.5 | 0.63 | 0.8 | 0.8 | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 |
| | 50 | | | | | | 0.63 | 0.8 | 0.8 | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 | |
| | 63 | | | | | | | 0.8 | 0.8 | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 | |
| | 80 | | | | | | | | 1.25 | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 | | |
| | 100 | | | | | | | | | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 | | |
| CVS160 B/F/N | 100 | | | | | | | | | | 1.25 | 1.25 | 1-2 | 1,25 - 2,5 | |
| TM•D | 125 | | | | | | | | | | | 1-2 | 1,25 - 2,5 | | |
| | 160 | | | | | | | | | | | | 1,25 - 2,5 | | |

 4 Selectivity limit = 4kA

 T Total selectivity, up to the breaking capacity of the downstream circuit breaker.

 No Selectivity

Nota: respect the basic rules of selectivity for overload and short-circuit. See Introduction

Selectivity

Upstream: EasyPact CVS320-600 F/N TM•D

Downstream: iK60N

$U_e \leq 415 \text{ Vac}$

| Upstream Trip Unit | | CVS320 F/N TM•D | | | | CVS400 F/N TM•D | | | | CVS500 F/N TM•D | | | | CVS600 F/N TM•D | | | |
|------------------------|-----------------|-----------------|-----|-----|-----|-----------------|-----|-----|-----|-----------------|-----|-----|-----|-----------------|-----|-----|-----|
| Downstream | Rating | 320 | | | | 400 | | | | 500 | | | | 600 | | | |
| | Setting Im (kA) | 225 | 255 | 290 | 320 | 280 | 320 | 360 | 400 | 350 | 400 | 450 | 500 | 420 | 480 | 540 | 630 |
| | 3.2 | 4 | | | | 5 | | | | 5 | | | | 5 | | | |
| | Im = 5- 10In | | | | | Im = 5- 10In | | | | Im = 5- 10In | | | | Im = 4- 8In | | | |
| Selectivity Limit (kA) | | | | | | | | | | | | | | | | | |
| iK60N | ≤ 10 | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T |
| B-C Curves | 16 | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T |
| 1P 230V | 20 | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T |
| 2,3,4P 400V | 25 | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T |
| | 32 | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T |
| | 40 | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T |
| | 50 | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T |
| | 63 | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T | T |

4 Selectivity limit = 4kA

Total selectivity, up to the breaking capacity of the downstream circuit breaker.

No Selectivity

Nota: respect the basic rules of selectivity for overload and short-circuit. See Introduction

Ue ≤ 415 Vac

| Upstream Trip Unit | | EasyPact CVS400 F/N ETS | | | | | | EasyPact CVS600 F/N ETS | | | | | | |
|---------------------------|----------------|-------------------------|-----|-----|-----|-----|-----|-------------------------|-----|-----|-----|-----|-----|-----|
| Downstream Rating Setting | Rating Setting | 400 | 250 | 280 | 320 | 360 | 400 | 630 | 315 | 400 | 440 | 500 | 570 | 630 |
| Im = 2- 10Ir i = 11In | | | | | | | | | | | | | | |
| iK60N | ≤ 10 | T | T | T | T | T | T | T | T | T | T | T | T | T |
| B-C Curves | 16 | 4 | T | T | T | T | T | T | T | T | T | T | T | T |
| 1P 230V | 20 | 4 | T | T | T | T | T | T | T | T | T | T | T | T |
| 2,3,4P 400V | 25 | 4 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 32 | 3.5 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 40 | 3.5 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 50 | 3 | 4 | T | T | T | T | T | T | T | T | T | T | T |
| | 63 | 3 | 4 | T | T | T | T | T | T | T | T | T | T | T |

4 Selectivity limit = 4kA

T Total selectivity, up to the breaking capacity of the downstream circuit breaker.

No Selectivity

Nota: respect the basic rules of selectivity for overload and short-circuit. See
Introduction

Selectivity

Upstream: EasyPact CVS320-600 F/N TM•D

Downstream: EasyPact CVS

Ue ≤ 415 Vac

| Upstream Trip Unit | | CVS320 F/N TM•D | | | | CVS400 F/N TM•D | | | | CVS500 F/N TM•D | | | | CVS600 F/N TM•D | | | |
|-----------------------|------------------------|--------------------|--------------|-----|-----|--------------------|-----|--------------|-----|--------------------|-----|-----|--------------|--------------------|-----|-----|-----|
| Downstream | Rating | 320 | 225 | 255 | 290 | 320 | 400 | 280 | 320 | 360 | 400 | 500 | 350 | 400 | 450 | 500 | 600 |
| | Ir (A) | | | | | | | | | | | | | | | 420 | 480 |
| | Im (kA) | 3.2 | | | | | 4 | | | | | 5 | | | | 540 | 630 |
| | | | Im = 5- 10In | | | | | Im = 5- 10In | | | | | Im = 5- 10In | | | | |
| | Selectivity Limit (kA) | | | | | | | | | | | | | | | | |
| CVS100 BS | 16 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 7 | 7 | 7 | 7 | 7 | 7 |
| TM•D | 20 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 6 | 6 | 6 | 6 | 6 | 6 |
| | 25 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 6 | 6 | 6 | 6 | 6 | 6 |
| | 32 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| | 40 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| | 50 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| | 63 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| | 80 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| | 100 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| CVS100 B/F/N | 16 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 7 | 7 | 7 | 7 | 7 | 7 |
| TM•D | 25 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 6 | 6 | 6 | 6 | 6 | 6 |
| | 32 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| | 40 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| | 50 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| | 63 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| | 80 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| | 100 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| CVS 160 B/F/N | 100 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| TM•D | 125 | 3.2 | 3.2 | 3.2 | 3.2 | 3.2 | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| | 160 | | | | | | 4 | 4 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| CVS 250 B/F/N | 160 | | | | | | 3.2 | 3.2 | 4 | 4 | 4 | 5 | 5 | 5 | 5 | 5 | 5 |
| TM•D | 200 | | | | | | | | | | | 4 | 4 | 5 | 5 | 5 | 5 |
| | 250 | | | | | | | | | | | 4 | 5 | 5 | 5 | 5 | 5 |
| CVS400 F/N | 320 | | | | | | | | | | | | | | | | 5 |
| TM-D | 400 | | | | | | | | | | | | | | | | 5 |
| CVS400 F/N ETS | 400 | | | | | | | | | | | | | | | | 5 |

4 Selectivity limit = 4kA

T Total selectivity, up to the breaking capacity of the downstream circuit breaker.

 No Selectivity

Nota: respect the basic rules of selectivity for overload and short-circuit. See Introduction

Ue ≤ 415 Vac

| Upstream Trip Unit | | EasyPact CVS400 F/N ETS | | | | | | EasyPact CVS600 F/N ETS | | | | | |
|------------------------|---------|----------------------------|-----|-----|-----|-----|-----|----------------------------|-----|-----|-----|-----|-----|
| Downstream | Rating | 400 | | | | | | 630 | | | | | |
| | Ir (A) | 200 | 250 | 280 | 320 | 360 | 400 | 315 | 400 | 440 | 500 | 570 | 630 |
| | Im (kA) | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 5 | 5.7 | 6.3 |
| Selectivity Limit (kA) | | Im = 2- 10Ir li = 11In | | | | | | Im = 2- 10Ir li = 11In | | | | | |
| EasyPact CVS100 BS | 16 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 5 | 7 | 10 | 15 |
| TM-D | 20 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 5 | 6 | 10 | 12 |
| | 25 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 5 | 6 | 10 | 12 |
| | 32 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 6 | 7 | 10 |
| | 40 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 6 | 7 | 10 |
| | 50 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 5.5 | 6.6 | 8 |
| | 63 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 5 | 5.7 | 7 |
| | 80 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 5 | 5.7 | 6.3 |
| | 100 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 5 | 5.7 | 6.3 |
| EasyPact CVS100 B/F/N | 16 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 5 | 7 | 10 | 15 |
| TM-D | 25 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 5 | 6 | 10 | 12 |
| | 32 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 6 | 7 | 10 |
| | 40 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 6 | 7 | 10 |
| | 50 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 5.5 | 6.6 | 8 |
| | 63 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 5 | 5.7 | 7 |
| | 80 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 5 | 5.7 | 6.3 |
| | 100 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 5 | 5.7 | 6.3 |
| CVS160 B/F/N | 100 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 5 | 5.7 | 6.3 |
| TM-D | 125 | 2 | 2.5 | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 5 | 5.7 | 6.3 |
| | 160 | | | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 5 | 5.7 | 6.3 |
| CVS250 B/F/N | 160 | | | 2.8 | 3.2 | 3.6 | 4 | 3.1 | 4 | 4.4 | 5 | 5.7 | 6.3 |
| TM-D | 200 | | | | | 3.6 | 4 | 3.1 | 4 | 4.4 | 5 | 5.7 | 6.3 |
| | 250 | | | | | | 4 | | 4 | 4.4 | 5 | 5.7 | 6.3 |
| CVS400 F/N TM-D | 320 | | | | | | | | | | | 5.7 | 6.3 |
| | 400 | | | | | | | | | | | | 6.3 |
| CVS400 F/N ETS | 400 | | | | | | | | | | | | 6.3 |

 Selectivity limit = 4kA

 Total selectivity, up to the breaking capacity of the downstream circuit breaker.

 No Selectivity

Note: respect the basic rules of selectivity for overload and short-circuit. See
Introduction

Ue ≤ 415 Vac

| Upstream Trip Unit | | Comapct NS 630-1600 N Micrologic 2 lsd = 10In | | | | | | Comapct NS 630-1600 N Micrologic 5,6 Inst 15In or OFF | | | | | |
|------------------------|--------------------------|--|-----|------|------|------|------|--|------|------|------|------|------|
| Downstream | Rating Setting Ir (A) | 630 | 800 | 1000 | 1250 | 1600 | 630 | 800 | 1000 | 1250 | 1600 | | |
| Selectivity Limit (kA) | | 400 | 630 | 800 | 1000 | 1250 | 1600 | 400 | 630 | 800 | 1000 | 1250 | 1600 |
| CVS 100 BS | 16 | T | T | T | T | T | T | T | T | T | T | T | T |
| TM+D | 20 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 25 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 32 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 40 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 50 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 63 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 80 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 100 | T | T | T | T | T | T | T | T | T | T | T | T |
| CVS 100 B/F/N | 16 | T | T | T | T | T | T | T | T | T | T | T | T |
| TM+D | 25 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 32 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 40 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 50 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 63 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 80 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 100 | T | T | T | T | T | T | T | T | T | T | T | T |
| CVS 160 B/F/N | 100 | T | T | T | T | T | T | T | T | T | T | T | T |
| TM+D | 125 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 160 | T | T | T | T | T | T | T | T | T | T | T | T |
| CVS 250 B/F/N | 160 | T | T | T | T | T | T | T | T | T | T | T | T |
| TM+D | 200 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 250 | T | T | T | T | T | T | T | T | T | T | T | T |
| CVS 400 F/N | 320 | T | T | T | T | T | T | T | T | T | T | T | T |
| TM+D | 400 | T | T | T | T | T | T | T | T | T | T | T | T |
| CVS 600 F/N | 500 | T | T | T | T | T | T | T | T | T | T | T | T |
| TM+D | 600 | T | T | T | T | T | T | T | T | T | T | T | T |
| CVS 400F/N | 320 | T | T | T | T | T | T | T | T | T | T | T | T |
| ETU | 400 | T | T | T | T | T | T | T | T | T | T | T | T |
| CVS 630F/N | 500 | T | T | T | T | T | T | T | T | T | T | T | T |
| ETU | 630 | T | T | T | T | T | T | T | T | T | T | T | T |

| Upstream Trip Unit | | Comapct NS 630-1600 N Micrologic 2 lsd = 10In | | | | | | Comapct NS 630-1600 N Micrologic 5,6 Inst 15In or OFF | | | | | |
|------------------------|--------------------------|--|-----|------|------|------|------|--|------|------|------|------|------|
| Downstream | Rating Setting Ir (A) | 630 | 800 | 1000 | 1250 | 1600 | 630 | 800 | 1000 | 1250 | 1600 | | |
| Selectivity Limit (kA) | | 400 | 630 | 800 | 1000 | 1250 | 1600 | 400 | 630 | 800 | 1000 | 1250 | 1600 |
| CVS 100 B/F | 2.5 | T | T | T | T | T | T | T | T | T | T | T | T |
| MA + O/L R | 6.3 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 12.5 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 25 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 50 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 100 | T | T | T | T | T | T | T | T | T | T | T | T |
| CVS 160 B/F | 100 | T | T | T | T | T | T | T | T | T | T | T | T |
| MA + O/L R | 150 | T | T | T | T | T | T | T | T | T | T | T | T |
| | 100 | T | T | T | T | T | T | T | T | T | T | T | T |
| CVS 250 B/F | 220 | T | T | T | T | T | T | T | T | T | T | T | T |
| MA + O/L R | | | | | | | | | | | | | |
| CVS 400 F/N | 320 | | | | | | | | | | | | |
| MA + O/L R | | | | | | | | | | | | | |
| CVS 600 F/N | 500 | | | | | | | | | | | | |
| MA + O/L R | | | | | | | | | | | | | |

4 Selectivity limit = 4kA

T Total selectivity, up to the breaking capacity of the downstream circuit breaker.

 No Selectivity

Nota: respect the basic rules of selectivity for overload and short-circuit. See
Introduction

What is cascading (or Back up Protection) ?

Cascading is the use of the current limiting capacity of circuit breakers at a given point to permit installation of lower-rated and therefore lower-cost circuit breakers downstream. The upstream circuit breakers acts as a barrier against short-circuit currents. In this way, downstream circuit breakers with lower breaking capacities than the prospective short-circuit (at their point of installation) operate under their normal breaking conditions. Since the current is limited throughout the circuit controlled by the limiting circuit breaker, cascading applies to all switchgear downstream. It is not restricted to two consecutive devices.

General use of cascading

With cascading, the devices can be installed in different switchboards. Thus, in general, cascading refers to any combination of circuit breakers where a circuit breaker with a breaking capacity less than the prospective I_{sc} at its point of installation can be used. Of course, the breaking capacity of the upstream circuit breaker must be greater than or equal to the prospective short-circuit current at its point of installation.

Coordination between circuit breakers

The use of a protective device possessing a breaking capacity less than the prospective short-circuit current at its installation point is permitted as long as another device is installed upstream with at least the necessary breaking capacity. In this case, the characteristics of the two devices must be coordinated in such a way that the energy let through by the upstream device is not more than that which can be withstood by the downstream device and the cables protected by these devices without damage. Cascading can only be checked by laboratory tests and the possible combinations can be specified only by the circuit breaker manufacturer.

Ue ≤ 415 Vac

| Upstream | | CVS100 | | | CVS100 | | | CVS160 | | | CVS250 | | | CVS400 | | CVS630 | |
|------------|---------------|--------|----|----|--------|----|----|--------|----|----|--------|----|----|--------|----|--------|---|
| Downstream | BS | B | F | N | B | F | N | B | F | N | B | F | N | F | N | F | N |
| | Icu (kA) 415V | 25 | 25 | 36 | 50 | 25 | 36 | 50 | 25 | 36 | 50 | 36 | 36 | 50 | 36 | 50 | |
| Downstream | | | | | | | | | | | | | | | | | |
| iK60N | 6 | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 36 | 36 | 36 | 36 | 36 | |
| CVS100BS | 25 | | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | |
| CVS100B | 25 | | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | 36 | |
| CVS100F | 36 | | | 50 | | 50 | | 50 | | 50 | | 50 | | 50 | | 50 | |
| CVS160B | 25 | | | 36 | | 36 | | 36 | | 36 | | 36 | | 36 | | 36 | |
| CVS160F | 36 | | | 50 | | 50 | | 50 | | 50 | | 50 | | 50 | | 50 | |
| CVS250B | 25 | | | | | | | | | | | 36 | 36 | 36 | 36 | 36 | |
| CVS250F | 36 | | | | | | | | | | | | 50 | 50 | 50 | 50 | |
| CVS400F | 36 | | | | | | | | | | | | 50 | 50 | 50 | 50 | |
| CVS400N | 50 | | | | | | | | | | | | | | | | |

Switch disconnector coordination

upstream: Circuit breaker **EasyPact CVS** or gG fuses

Downstream: Switch disconnector **EasyPact CVS NA**

| Switch disconnector Compact NA | CVS100NA | CVS160NA | CVS250NA | CVS400NA | CVS630NA |
|------------------------------------|-------------|-------------|-------------|-------------|-------------|
| Upstream protection = CVS | | | | | |
| type / rating (A) | CVS100B/100 | CVS160B/160 | CVS250B/250 | | |
| Conditionnal short circuit current | 25 | 25 | 25 | | |
| making current | kA rms | | | | |
| | 53 | 53 | 53 | | |
| making current | kA peak | | | | |
| type / rating (A) | CVS100F/100 | CVS160F/160 | CVS250F/250 | CVS400F/400 | CVS630F/630 |
| Conditionnal short circuit current | 36 | 36 | 36 | 36 | 36 |
| making current | kA rms | | | | |
| | 76 | 76 | 76 | 76 | 76 |
| making current | kA peak | | | | |
| type / rating (A) | CVS100N/100 | CVS160N/160 | CVS250N/250 | CVS400N/400 | CVS630N/630 |
| Conditionnal short circuit current | 50 | 50 | 50 | 50 | 50 |
| making current | kA rms | | | | |
| | 105 | 105 | 105 | 105 | 105 |
| making current | kA peak | | | | |
| type / rating (A) | | | | CVS400H/400 | CVS630H/630 |
| Conditionnal short circuit current | | | | 70 | 70 |
| making current | | | | 154 | 154 |
| making current | | | | | |
| Upstream protection = gG fuses | | | | | |
| type / rating (A) | gG 80 | gG 125 | gG 200 | gG 315 | gG 500 |
| Conditionnal short circuit current | 100 | 100 | 100 | 100 | 100 |
| making current | kA rms | | | | |
| | 220 | 220 | 220 | 220 | 220 |
| making current | kA peak | | | | |



Catalogue numbers



Catalogue numbers

Functions and characteristics
Installation recommendations
Dimensions and connection
Additional characteristics

A-1
B-1
C-1
D-1

EasyPact CVS100 to 250

E-3

EasyPact CVS400 to 630

E-13

EasyPact CVS100BS

F-1

EasyPact CVS100 to 250

| | |
|---|-------------------|
| CVS100/160/250B: complete fixed/FC device EasyPact CVS100/160/250B with TM-D, TM-G (25kA 380/415 V) | E-3 E-3 |
| CVS100/160/250F: complete fixed/FC device EasyPact CVS100/160/250F with TM-D, MA (36kA 380/415 V) | E-4 E-4 |
| CVS100/160/250N: complete fixed/FC device EasyPact CVS100/160/250N with TM-D, MA (50kA 380/415 V) | E-5 E-5 |
| CVS100/160/250NA: complete fixed/FC device EasyPact CVS100/160/250NA | E-6 E-6 |
| Add-on Vigi module: EasyPact and Vigi CVS100/160/250 | E-7 E-7 |
| Accessories EasyPact and Vigi CVS100/160/250 | E-8 E-8 |


CVS100/160/250B: complete fixed/FC device

EasyPact CVS100/160/250B (25 kA 380/415 V)

DB400150

EasyPact CVS100/160/250B

With TM-D thermal-magnetic trip unit



EasyPact CVS100B (25 kA at 380/415 V)

| | | | |
|--------|----------|----------|----------|
| Rating | 3P 3d | 4P 3d | 4P 4d |
| TM16D | LV510300 | LV510310 | LV510321 |
| TM25D | LV510301 | LV510311 | LV510322 |
| TM32D | LV510302 | LV510312 | LV510323 |
| TM40D | LV510303 | LV510313 | LV510324 |
| TM50D | LV510304 | LV510314 | LV510325 |
| TM63D | LV510305 | LV510315 | LV510326 |
| TM80D | LV510306 | LV510316 | LV510327 |
| TM100D | LV510307 | LV510317 | |

EasyPact CVS160B (25 kA at 380/415 V)

| | | | |
|--------|----------|----------|----------|
| Rating | 3P 3d | 4P 3d | 4P 4d |
| TM100D | LV516301 | LV516311 | LV516322 |
| TM125D | LV516302 | LV516312 | LV516323 |
| TM160D | LV516303 | LV516313 | |


EasyPact CVS250B (25 kA at 380/415 V)

| | | | |
|--------|----------|----------|----------|
| Rating | 3P 3d | 4P 3d | 4P 4d |
| TM160D | LV525301 | LV525312 | LV525322 |
| TM200D | LV525302 | LV525313 | LV525323 |
| TM250D | LV525303 | | |

DB400150

EasyPact CVS160/250B

With TM-G thermal-magnetic trip unit



EasyPact CVS160B (25 kA at 380/415 V)

| | | |
|--------|----------|----------|
| Rating | 3P 3d | 4P 3d |
| TM80G | LV510736 | LV510748 |
| TM100G | LV510737 | LV510749 |
| TM125G | LV516732 | LV516742 |
| TM160G | LV516733 | LV516743 |

EasyPact CVS250B (25 kA at 380/415 V)

| | | |
|--------|----------|----------|
| Rating | 3P 3d | 4P 3d |
| TM200G | LV525732 | LV525742 |
| TM250G | LV525733 | LV525743 |


CVS100/160/250F: complete fixed/FC device

EasyPact CVS100/160/250F (36 kA 380/415 V)

EasyPact CVS100/160/250F

With TM-D thermal-magnetic trip unit

DB400150



EasyPact CVS100F (36 kA at 380/415 V)

| Rating | 3P 3d | 4P 3d | 4P 4d |
|--------|----------|----------|----------|
| TM16D | LV510330 | LV510340 | |
| TM25D | LV510331 | LV510341 | |
| TM32D | LV510332 | LV510342 | LV510352 |
| TM40D | LV510333 | LV510343 | LV510353 |
| TM50D | LV510334 | LV510344 | LV510354 |
| TM63D | LV510335 | LV510345 | LV510355 |
| TM80D | LV510336 | LV510346 | LV510356 |
| TM100D | LV510337 | LV510347 | LV510357 |

EasyPact CVS160F (36 kA at 380/415 V)

| Rating | 3P 3d | 4P 3d | 4P 4d |
|--------|----------|----------|----------|
| TM100D | LV516331 | LV516341 | |
| TM125D | LV516332 | LV516342 | LV516352 |
| TM160D | LV516333 | LV516343 | LV516353 |


EasyPact CVS250F (36 kA at 380/415 V)

| Rating | 3P 3d | 4P 3d | 4P 4d |
|--------|----------|----------|----------|
| TM160D | LV525331 | | |
| TM200D | LV525332 | LV525342 | LV525352 |
| TM250D | LV525333 | LV525343 | LV525353 |

EasyPact CVS100/160/250F

With MA magnetic trip unit

DB400150



EasyPact CVS100F (36 kA at 380/415 V)

| Rating | 3P 3d |
|--------|----------|
| MA2.5 | LV510440 |
| MA6.3 | LV510441 |
| MA12.5 | LV510442 |
| MA25 | LV510443 |
| MA50 | LV510444 |
| MA100 | LV510445 |

EasyPact CVS160F (36 kA at 380/415 V)

| Rating | 3P 3d |
|--------|----------|
| MA100 | LV516439 |
| MA150 | LV516440 |

EasyPact CVS250F (36 kA at 380/415 V)


| Rating | 3P 3d |
|--------|----------|
| MA220 | LV525439 |

CVS100/160/250N: complete fixed/FC device

EasyPact CVS100/160/250N (50 kA 380/415 V)

EasyPact CVS160/250N

With TM-D thermal-magnetic trip unit



DB400150

EasyPact CVS100N (50 kA at 380/415 V)

| Rating | 3P 3d | 4P 3d |
|--------|----------|----------|
| TM16D | LV510470 | LV510480 |
| TM25D | LV510471 | LV510481 |
| TM32D | LV510472 | LV510482 |
| TM40D | LV510473 | LV510483 |
| TM50D | LV510474 | LV510484 |
| TM63D | LV510475 | LV510485 |
| TM80D | LV510476 | LV510486 |
| TM100D | LV510477 | LV510487 |

EasyPact CVS160N (50 kA at 380/415 V)


| Rating | 3P 3d | 4P 3d |
|--------|----------|----------|
| TM100D | LV516461 | LV516466 |
| TM125D | LV516462 | LV516467 |
| TM160D | LV516463 | LV516468 |

EasyPact CVS250N (50 kA at 380/415 V)

| Rating | 3P 3d | 4P 3d |
|--------|----------|----------|
| TM200D | LV525452 | LV525457 |
| TM250D | LV525453 | LV525458 |

EasyPact CVS100/160/250N

With MA magnetic trip unit



DB400150

EasyPact CVS100N (50 kA at 380/415 V)

| Rating | 3P 3d |
|--------|----------|
| MA2.5 | LV510450 |
| MA6.3 | LV510451 |
| MA12.5 | LV510452 |
| MA25 | LV510453 |
| MA50 | LV510454 |
| MA100 | LV510455 |

EasyPact CVS160N (50 kA at 380/415 V)

| Rating | 3P 3d |
|--------|----------|
| MA100 | LV516450 |
| MA150 | LV516451 |

EasyPact CVS250N (50 kA at 380/415 V)


| Rating | 3P 3d |
|--------|----------|
| MA220 | LV525442 |

CVS100/160/250NA: complete fixed/FC device

EasyPact CVS100/160/250NA

EasyPact CVS100/160/250NA switch-disconnector

With NA switch-disconnector unit



DB40155

EasyPact CVS100NA

| | | |
|--------|----------|----------|
| Rating | 3P | 4P |
| 100 | LV510425 | LV510426 |


EasyPact CVS160NA

| | | |
|--------|----------|----------|
| Rating | 3P | 4P |
| 160 | LV516425 | LV516426 |

EasyPact CVS250NA

| | | |
|--------|----------|----------|
| Rating | 3P | 4P |
| 250 | LV525425 | LV525426 |


DB11464

+ Vigi module**Vigi module**



| | 3P | 4P |
|---------------------------|----------|----------|
| CVS100/160 (220 to 440 V) | LV429210 | LV429211 |
| CVS250 (220 to 440 V) | LV431535 | LV431536 |

Connection accessories (Cu or Al)


Rear connections

| | | | | |
|----------|--|--|--|----------|
| DB112225 |  2 short 2 long | | | LV429235 |
| | | | | LV429236 |

Bare cable connectors




| | | | | |
|----------|---|---|-----------|----------|
| DB112226 |  Steel connectors | 1 x (1.5 to 95 mm ²) ; ≤ 160 A | Set of 3 | LV429242 |
| | | | Set of 4 | LV429243 |
| DB112225 |  Aluminium connectors | 1 x (25 to 95 mm ²) ; ≤ 250 A | Set of 3 | LV429227 |
| | | 1 x (120 to 185 mm ²) ; ≤ 250 A | Set of 4 | LV429228 |
| DB112726 |  Clips for connectors | | Set of 3 | LV429259 |
| | | | Set of 4 | LV429260 |
| DB112227 |  Aluminium connectors for 2 cables ⁽¹⁾ | 2 x (50 to 120 mm ²) ; ≤ 250 A | Set of 3 | LV429218 |
| | | | Set of 4 | LV429219 |
| DB112724 |  6.35 mm voltage tap for steel or aluminium connectors | | Set of 10 | LV429348 |

Terminal extensions

| | | | |
|----------|--|----------|----------|
| DB112235 |  Spreaders from 35 to 45 mm pitch ⁽¹⁾ | Set of 3 | LV431563 |
| | | Set of 4 | LV431564 |

⁽¹⁾ Supplied with 2 or 3 interphase barriers.

Insulation accessories

| | | | | |
|----------|--|--|------------|----------------------|
| DB112238 |  | 1 short terminal shield for breaker | 3 P 4 P | LV429515 LV429516 |
| DB400045 |  | 1 long terminal shield for breaker | 3 P 4 P | LV429517 LV429518 |
| DB400061 |  | Interphase barriers for breaker | Set of 6 | LV429329 |
| DB400163 |  | 2 insulating screens for breaker (45 mm pitch) | 3P 4P | LV429330 LV429331 |

(1) Supplied with 2 or 3 interphase barriers.

Electrical auxiliaries

| Auxiliary contacts (changeover) | | |
|---------------------------------|----------------------------------|-------|
| DB112254 | OF or SD or SDE or SDV | 29450 |
| | OF or SD or SDE or SDV low level | 29452 |


| | | |
|--------------|---|----------|
| CB8500821-00 | SDE adaptor, mandatory for trip unit TM, MA | LV429451 |
|--------------|---|----------|

| Voltage releases | | | |
|------------------|---------|--|----------------------------------|
| | Voltage | MX | MN |
| DB111464 | AC | 110-130 V 50/60 Hz 220-240 V 50/60 Hz and 208-277 V 60 Hz | LV429386 LV429387 |
| | DC | 24 V | LV429390 |
| | | | LV429406 LV429407 LV429410 |

Rotary handles

Direct rotary handle

DB112259




With black handle

LV429337

Extended rotary handle

DB112260




With black handle

LV429338

Locks

Toggle locking device for 1 to 3 padlocks


DB400164



By removable device

29370

DE400165




By fixed device

29371

Locking of rotary handle

DB112263



Keylock adaptor (keylock not included)
Keylock (keylock adaptor not included)

Ronis 1351B.500
Profalux KS5 B24 D4Z

LV429344
41940
42888

EasyPact CVS400 to 630

CVS400/630: complete fixed/FC device

E-13

- EasyPact CVS400/630F with TM-D (36 kA 380/415 V) E-13
- EasyPact CVS400/630N with TM-D (50 kA 380/415 V) E-13
- EasyPact CVS400/630F/N with MA (36/50 kA 380/415 V) E-13
- EasyPact CVS400/630F/N with ETS2.3 (36/50 kA 380/415 V) E-14
- EasyPact CVS400/630NA switch-disconnector E-14
- Add-on Vigi module: EasyPact and Vigi E-14

Accessories

E-15

- EasyPact and Vigi CVS400/630 E-15


CVS400/630:

complete fixed/FC device

EasyPact CVS400/630F/N (36/50 kA 380/415 V)

EasyPact CVS400/630F

With TM-D thermal-magnetic trip unit




DB400008

EasyPact CVS400F (36 kA at 380/415 V)

| | | | |
|--|----------|----------|----------|
| Rating | 3P 3d | 4P 3d | 4P 4d |
| TM320D | LV540305 | LV540308 | LV540311 |
| TM400D | LV540306 | LV540309 | LV540312 |
| EasyPact CVS630F (36 kA at 380/415 V) | | | |
| Rating | 3P 3d | 4P 3d | 4P 4d |
| TM500D | LV563305 | LV563308 | LV563311 |
| TM600D | LV563306 | LV563309 | LV563312 |

EasyPact CVS400/630N

With TM-D thermal-magnetic trip unit




DB400008

EasyPact CVS400N (50 kA at 380/415 V)

| | | | |
|--|----------|----------|----------|
| Rating | 3P 3d | 4P 3d | 4P 4d |
| TM320D | LV540315 | LV540318 | LV540322 |
| TM400D | LV540316 | LV540319 | |
| EasyPact CVS630N (50 kA at 380/415 V) | | | |
| Rating | 3P 3d | 4P 3d | 4P 4d |
| TM500D | LV563315 | LV563318 | LV563321 |
| TM600D | LV563316 | LV563319 | LV563322 |

EasyPact CVS400/630F/N

With MA magnetic trip unit



DB400020

EasyPact CVS400F (36 kA at 380/415 V)


| | |
|--|----------|
| Rating | 3P 3D |
| MA320 | LV540550 |
| EasyPact CVS400N (50 kA at 380/415 V) | |
| Rating | LV540552 |
| EasyPact CVS630F (36 kA at 380/415 V) | |
| Rating | LV563550 |
| EasyPact CVS630N (50 kA at 380/415 V) | |
| Rating | LV563552 |

CVS400/630: complete fixed/FC device

EasyPact CVS400/630F/N
(36/50 kA 380/415 V)

EasyPact CVS400/630FETS 2.3 electronic trip unit (LS₀I protection)

DB400021




| | |
|---------------------------------------|-------|
| EasyPact CVS400F (36 kA at 380/415 V) | 400 A |
| EasyPact CVS630F (36 kA at 380/415 V) | 630 A |

3P 3d
LV540505
LV563505

4P 3d, 4d, 3d + N/2
LV540506
LV563506

EasyPact CVS400/630NETS 2.3 electronic trip unit (LS₀I protection)

DB400021



| | |
|---------------------------------------|-------|
| EasyPact CVS400N (50 kA at 380/415 V) | 400 A |
| EasyPact CVS630N (50 kA at 380/415 V) | 630 A |


3P 3d
LV540510
LV563510

4P 3d, 4d, 3d + N/2
LV540511
LV563511

EasyPact CVS400/630 NA switch-disconnector

NA switch disconnector

DB400023




| | | |
|--------------------|----|----------|
| EasyPact CVS400 NA | 3P | LV540400 |
| EasyPact CVS630 NA | 4P | LV563400 |

4P
LV540401
LV563401

+ Vigi module

Vigi module

DB111464



| | | |
|--------------------------|----|----------|
| CVS400/630(200 to 440 V) | 3P | LV432455 |
| | 4P | LV432456 |


4P
LV432456

| Connection accessories (Cu or Al) | | | | |
|--|---|---|----------------------|--|
| Rear connections | | | | |
| DB11225 |  | 2 short 2 long | | LV432475 LV432476 |
| E22040 |  | Aluminium connector 1x (35 to 300 mm²) | Set of 3 Set of 4 | LV432479 LV432480 |
| E22041 |  | Aluminium connector 2x (35 to 240 mm²) | Set of 3 Set of 4 | LV432481 LV432482 |
| | | Voltage plug for aluminium connector 1 or 2 cables | Set of 10 | LV429348 |
| Terminal extension ⁽¹⁾ | | | | |
| E21012 |  | Spreaders | 52.5 mm 70 mm | 3P 4P 3P 4P |
| | | | | LV432490 LV432491 LV432492 LV432493 |
| Insulation accessories | | | | |
| E18618 |  | Short terminal shield, 45 mm (1 piece) | 3P 4P | LV432591 LV432592 |
| | | Long terminal shield, 45 mm (1 piece) | 3P 4P | LV432593 LV432594 |
| E18906 |  | Interphase barriers | Set of 6 | LV432570 |
| | | Long terminal shield for spreaders, 52,5mm (1 piece) (supplied with insulating plate) | 3P 4P | LV432595 LV432596 |
| | | 2 insulating screens (70 mm pitch) | 3P 4P | LV432578 LV432579 |

⁽¹⁾ supplied with 2 or 3 interphase barriers

Electrical auxiliaries

Auxiliary contacts (changeover)



E18608

CDB500821-00

OF or SD or SDE or SDV

OF or SD or SDE or SDV low level


29450

29452

SDE adaptor mandatory for trip unit TM, MA and ETS2.3

LV540050

Voltage releases



E18609

Voltage

AC 110-130 V 50/60 Hz

AC 220-240 V 50/60 Hz and 208-277 V 60 Hz

DC 24 V

MX

LV429386

LV429387

LV429390

MN

LV429406


LV429407

LV429410

Rotary handle

Direct rotary handle

E18611




Standard black handle

LV432597

Extended rotary handle

E18612




Standard extended rotary handle

LV432598

Locks

Toggle locking device for 1 to 3 padlocks


E18621



By removable device

29370

E18613



By fixed device

32631

Locking of the rotary handle

E18620



Keylock adaptor (keylock not included)

Keylock (keylock adaptor not included)

Ronis 1351B.500

Profalux KS5 B24 D4Z

LV432604

41940

42888

EasyPact™ CVS100BS



EasyPact CVS100BS

| | |
|--------------------------------------|-----|
| <i>Functions and characteristics</i> | A-1 |
| <i>Installation recommendations</i> | B-1 |
| <i>Dimensions and connection</i> | C-1 |
| <i>Additional characteristics</i> | D-1 |
| <i>Catalogue numbers</i> | E-1 |

| | |
|---------------------|------------|
| Presentation | F-2 |
| EasyPact CVS100BS | F-2 |


| | |
|---------------------|------------|
| Overview | F-3 |
| Optimal Combination | F-3 |

| | |
|--|------------|
| Functions and Characteristics | F-4 |
| General characteristics | F-4 |
| Protection of LV Power Distribution System | |
| EasyPact CVS100BS | F-5 |
| Installation and Connection | |
| EasyPact CVS100BS | F-6 |
| Electrical and Mechanical Accessories | |
| EasyPact CVS100BS | F-7 |

| | |
|--------------------------------------|------------|
| Technical Data Supplement | F-9 |
| Tripping Curve EasyPact CVS100BS | |
| Power Distribution Protection System | F-9 |
| Temperature and Altitude Derating | |
| Current-limiting | F-11 |
| Capacitor protection | F-12 |
| | F-13 |

| | |
|--------------------------|-------------|
| Catalogue numbers | F-14 |
| EasyPact CVS100BS | F-14 |
| Accessories | F-15 |

| | |
|------------------------------------|-------------|
| Dimensions and Installation | F-17 |
| EasyPact CVS100BS | F-17 |
| Accessories EasyPact CVS100BS | F-19 |



EasyPact CVS100BS

Simplicity and perfection – That's what Schneider Electric brings to you. EasyPact CVS100BS not only reflects high quality of Schneider Electric, but also features performance, protection functions, and performance/price ratio.

EasyPact CVS100BS


- up to 100A 3 Pole/4 Pole products
- Icu 25kA, Ics 17kA
- Reliable protections of power distribution systems
- Flexible installation solutions including fixed, plug-in types
- Complete solutions for AC and DC networks

More reliable and safer

Powerful current-limiting capacity to ensure more cost-effective and more reliable protection.

Modularized System

As shown below, a wide range of modules or accessories are available.



1. Breaking unit
2. MN and MX voltage releases
3. Direct rotary handle
4. Extended rotary handle
5. Short terminal shield
6. Long terminal shield
7. Connection accessories

PB106445



EasyPact CVS100BS

Compliance with standards

- IEC 60947-1: General rules (GB/T 14048.1)
- IEC 60947-2: Circuit Breakers (GB/T 14048.2)
- IEC 60947-4: Contactors and Motor Starters (GB 14048.4)
- IEC 60946-5.1: Control circuit devices and Switching elements; automatic Control Components (GB 14048.5)

Tropicalization

EasyPact CVS100BS circuit breakers have successfully passed the tests prescribed by following standards for extreme atmospheric conditions:

- IEC 68-2-30, damp heat(95% relative humidity at 55°C)
- QIEC 68-2-52 Salt mist (severity level 2)

Positive contact indication

All EasyPact CVS100BS circuit breakers are suitable for isolation as defined in IEC standard 60947-2:

- the isolation position corresponds to the O (OFF) position
- the operating handle cannot indicate the "OFF" position unless the contacts are effectively open
- padlocks may not be installed unless the contacts are open

Installation of a rotary handle or a motor mechanism does not alter the reliability of the position-indication system.

The isolation function is certified by tests guaranteeing:

- the mechanical reliability of the position indication system
- the absence of leakage currents
- overvoltage withstand capacity between upstream and downstream connections




PB106445



EasyPact CVS100BS

| EasyPact circuit breaker | | | CVS100BS |
|--|-----------------------------------|----------------------------------|--------------------------|
| Number of Poles | | | 3, 4 |
| Control | Manual | Toggle | ■ |
| Connection | Fixed | Direct or extended rotary handle | ■ |
| | Plug-in | Front connection | ■ |
| Electrical characteristics as per IEC 60947-2 and EN 60947-2 | | | |
| Rated current (A) | In | 40°C | 100 |
| Rated insulation voltage (V) | Ui | | 690 |
| Rated impulse withstand voltage (kV) | Uimp | | 6 |
| Rated operational voltage (V) | Ue | AC 50/60 Hz | 440 |
| | | DC | |
| Circuit breaker type | | | BS |
| Ultimate breaking capacity (kA rms) | Icu | AC 50/60 Hz | 50 |
| | | 380/400 V | 25 |
| | | 415 V | 25 |
| Service breaking capacity (kA) | Ics | 220/230 V | 25kA |
| | | 380/400 V | 17kA |
| Suitability for Isolation | | | ■ |
| Utilisation category | | | A |
| Durability (C-O cycles) | Mechanical | | 13000 |
| | Electrical | 415 V | 4000 |
| Protection | | | |
| Trip units | | Thermal-magnetic | |
| Overload protection | Long time | Ir (In x ...) | 0.8 to 1xIn |
| Short-circuit protection | Short time | Isd (Ir x ...) | - |
| | Instantaneous | li (In x ...) | ■ |
| Indication and control auxiliaries | | | |
| Auxiliary switch | | | ■ |
| MX shunt release | | | ■ |
| MN under-voltage release | | | ■ |
| Installation | | | |
| Accessories | Terminal extensions and spreaders | | - |
| | Terminal shields | | ■ |
| | interphase barriers | | ■ |
| Dimensions (mm) WxHxD | Fixed, front connection 3P/4P | | 75x130x60/ 100x130x60 |
| Weight (kg) | Fixed, front connection 3P/4P | | 0.78/1.0 |




EasyPact CVS100BS

Connection of electrical auxiliaries

Fixed configuration

Auxiliary circuits exit the device through a knock-out in the front cover.



Each auxiliary device is equipped with a terminal block with numbered terminals for connection of wires up to:

- 1.5mm² for auxiliary contacts and voltage releases



EasyPact CVS100BS auxiliary contacts

EasyPact CVS100BS auxiliary switch

This auxiliary contacts can display the status of circuit breakers remotely, and therefore can be used for indications electrical interlocking, relay control. etc.

Functions

- OF (On/off): Indicate the position of circuit breaker contacts.
- SD (Trip indication): Indicate trip conditions of circuit breakers due to: overload, short-circuit, under-voltage or operation of the "push to trip" button. It returns to de-energised state when the circuit breaker is reset.

EasyPact CVS100BS multifunctional auxiliary switch

- OF/SD (Auxiliary + alarm): Indicate position of circuit breaker contacts and trip conditions of circuit breakers.

Standard

These auxiliary contacts comply with IEC 60947-5.

Installation and connection

- This auxiliary contacts clip into the slot behind the front cover of the circuit breaker.
- The conductor connected to the central terminal block has a cross-section up to 1.0mm².

All auxiliary contacts can be used to switch on/off electronic loads.

| Electrical characteristics | | In: 100A |
|----------------------------|------------------------------|------------------|
| Rated thermal current (A) | 5 | |
| Minimum load | 10mA, 24V | |
| Utilisation (IEC 947-4-1) | AC12 | AC15 |
| Operating current (A) | 110V 220~240V 380~440V | 5 3 2 - |

Voltage tripping

The voltage releases can trip the circuit breaker.

Under-voltage release (MN) trips the circuit breaker:

- When the tripping threshold drops below the rated voltage of the trip unit.
- The tripping threshold is 0.35 to 0.7 times the rated voltage.
- If the circuit breaker can be closed when the voltage exceeds 0.85 times the rated voltage.

Circuit breaker tripping by an MN release meets the requirements of standard IEC60947-2.

Shunt releases (MX)

The circuit breaker will trip by this release if the control voltage exceeds $0.7 \times U_n$. Control signals can be of the impulse type (≥ 20 ms) or maintained.

Operation

- The circuit breaker can be reset locally or remotely after tripping by an MN or MX release.
- MN or MX tripping is faster than manual tripping (or trip by electric mechanism). In the presence of a standing trip order, other operations will not be executed.
- Endurance:
 - EasyPact CVS100BS circuit breaker, typically 50% of the rated mechanical endurance of the circuit breaker

Installation and connection

- The circuit breaker panel has MX and MN releases at the rear part.
- Connection using wires up to 1.5mm².

| For EasyPact CVS100BS | | EasyPact CVS100BS | |
|-----------------------|-------------------|-------------------|-------|
| | | AC | DC |
| Consumption | Pick-up (MX) | < 10VA | < 10W |
| | Seal-in (MN, MNR) | < 5VA | < 5W |
| Response time (ms) | | < 50 | < 50 |

Note: 1. CVS100BS: select any two from three auxiliary switches (OF, SD, OF/SD).



EasyPact CVS100BS Voltage Release



EasyPact CVS100BS with a direct rotary handle

Rotary handle

Two types of rotary handle are available:

- Direct rotary handle
- Extended rotary handle

Direct rotary handle

Protection degree: IP40, IK07, IP54

Operation

- Function:
 - Suitability for isolation
 - Indications of three positions including O (OFF), I (ON) and Tripped
 - Access to "push-to-trip" button
 - Circuit breaker locking capability in the OFF position by 1 to 3 padlocks, with a shackle diameter 5 to 8 mm (not supplied)

Installation

The front cover of the circuit breaker can be removed and replaced by the extended handle.

EasyPact CVS100BS series

The direct rotary handle is used in the following cases:

- Switchboards in motor control center (MCC):
 - Circuit-breaker closing is disabled if the door is open.
 - Door opening is disabled when the circuit breaker is ON.
 - Protection degree: IP43, IK07 (IP54, IK08)
 - Machine tool control, in compliance with CNOMO E03.81.501N, with a protection degree of IP54, IK08

Extended rotary handle

The circuit breaker on the switch cabinet can be operated with the rotary handle on the front.

Protection degree: IP55, IK08, IP54

Operation Functions:

- Suitability for isolation
- Indications of three positions including O (OFF), I (ON) and Tripped
- Access to trip unit settings, when the switchboard door is open.
- Circuit breaker closing is disabled if the door is open.
- Circuit breaker locking capability in the OFF position by 1 to 3 padlocks, with a shackle diameter 5 to 8 mm (not supplied). These are used to prevent the door from being opened.

The extended rotary handle is made up of:

- A unit that replaces the front cover of the circuit breaker ⁽¹⁾.
- An assembly (handle and front plate) on the door that is always secured in the same position, whether the circuit breaker is horizontally or vertically installed.
- An extension shaft that must be adjusted to the distance. The distance between the back of the circuit breaker and door is:
 - EasyPact CVS100BS: 145~422mm




EasyPact CVS100BS with an extended rotary handle


Tripping Curve EasyPact CVS100BS

Power Distribution Protection System


16 A




20 A




25 A




32 A



40 A




50 A




**Tripping Curve EasyPact
CVS100BS**
Power Distribution Protection System

63 A



80 A



100 A



Temperature derating of trip units

EasyPact CVS100BS


| Rating (A) | 40°C | 45°C | 50°C | 55°C | 60°C | 65°C | 70°C |
|------------|-------|-------|-------|------|------|------|------|
| 16 | 16.7 | 16.3 | 16.0 | 15.7 | 15.6 | 15.1 | 14.7 |
| 20 | 20.4 | 20.2 | 20.0 | 19.7 | 19.2 | 18.9 | 18.5 |
| 25 | 25.7 | 25.3 | 25.0 | 24.7 | 24.5 | 24.3 | 24.0 |
| 32 | 33.5 | 32.7 | 32.0 | 31.4 | 31.0 | 30.4 | 29.9 |
| 40 | 40.9 | 40.4 | 40.0 | 39.5 | 38.0 | 37.6 | 37.1 |
| 50 | 52.1 | 51.0 | 50.0 | 49.3 | 48.1 | 47.3 | 46.6 |
| 63 | 64.9 | 63.9 | 63.0 | 62.0 | 60.4 | 59.4 | 58.5 |
| 80 | 82.2 | 81.1 | 80.0 | 78.6 | 77.3 | 76.7 | 76.1 |
| 100 | 103.0 | 101.0 | 100.0 | 99.0 | 94.0 | 94.0 | 93.0 |

Altitude Derating of trip units

Altitude does not significantly affect circuit-breaker characteristics up to 2000 m. Above this altitude, it is necessary to take into account the decrease in the dielectric strength and cooling capacity of air. It should be noted that the breaking capacity remained unchanged.

| EasyPact CVS100BS | 2000 | 2600 | 3900 |
|-------------------------------|----------------|-------------------|------------------|
| Height (m) | 2000 | 2600 | 3900 |
| Dielectric strength (V) | 3000 | 2850 | 2400 |
| Maximum operation voltage (V) | 690 | 655.5 | 552 |
| Nominal current at 40°C (A) | $1 \times I_n$ | $0.95 \times I_n$ | $0.8 \times I_n$ |

Current-limiting capacity refers to the ability of a circuit breaker to limit short-circuit current.



Ics 17kA

Current-limiting performance of EasyPact CVS100BS series helps lower power generated by fault current, and consequently improves the breaking capacity of the circuit-breaker. Ics 17kA.

Extension of service life of electrical installation

Circuit breaker current-limiting technology greatly reduces damage to installation caused by short-circuit current.

Thermal effect

Lowers temperature rise and extend the service life of the cable.

Mechanical effect

Risks of contact and busbar distortion and damage are greatly reduced since the electrodynamic force is decreased.

Electromagnetic effect

Disturbance on surrounding measurement instrument is relieved.

Current-limiting curve

Current-limiting capacity of a circuit breaker can be represented by two curves. It varies with the value of prospective short-circuit current (short-circuit current without any protective device).



- Actual peak current (current-limiting)
- Thermal effect (A^2s), which means energy loss of a 1Ω conductor carrying the short-circuit current.

Maximum allowable thermal stress of cable

The maximum allowable overheat values (in A^2s), dependent on cable insulation material (Cu or Al) and cross-section (mm^2), are listed in the following table.


| Cross section (mm^2) | | 1.5 | 2.5 | 4 | 6 | 10 |
|--------------------------|----------|--------------------|--------------------|--------------------|--------------------|--------------------|
| PVC | Copper | 2.97×10^4 | 8.26×10^4 | 2.12×10^5 | 4.76×10^5 | 1.32×10^6 |
| | Aluminum | - | - | - | - | 5.41×10^5 |
| PRC | Copper | 4.10×10^4 | 1.39×10^5 | 2.92×10^5 | 6.56×10^5 | 1.82×10^6 |
| | Aluminum | - | - | - | - | 7.52×10^5 |
| Cross section (mm^2) | | 16 | 25 | 35 | 50 | |
| PVC | Copper | 3.4×10^6 | 8.26×10^6 | 1.62×10^7 | 3.31×10^7 | |
| | Aluminum | 1.39×10^6 | 3.38×10^6 | 6.64×10^6 | 1.35×10^7 | |
| PRC | Copper | 4.69×10^6 | 1.39×10^7 | 2.23×10^7 | 4.56×10^7 | |
| | Aluminum | 1.93×10^6 | 4.70×10^6 | 9.23×10^6 | 1.88×10^7 | |

Current-limiting curves of EasyPact CVS100BS





EasyPact CVS100BS



EasyPact CVS100BS circuit breaker is suitable for capacitor protection following the rules below:

■ **Inc = Nominal current of the capacitor**

$$I_{nc} = \frac{Q_c}{U\sqrt{3}}$$

Inc = Nominal Current Capacitor (A)
Qc = Reactive power (kVAR)
U = Nominal Voltage (V)

■ **Inb = Nominal current of the circuit breaker**

- Inb = $1.36 \times I_{nc}$ for standard equipment
- Inb = $1.5 \times I_{nc}$ for overrated type equipment
- Inb = $1.12 \times I_{nc}$ for detuned type equipment: 2.7 tuning
- Inb = $1.19 \times I_{nc}$ for detuned type equipment: 3.8 tuning
- Inb = $1.31 \times I_{nc}$ for detuned type equipment: 4.3 tuning
- the short-circuit (magnetic) protection-setting thresholds must enable passage of the energising transients: $10 \times I_{nc}$ for standard, overrated and detuned type equipment.

■ **Icu = Ultimate breaking capacity of the circuit breaker**

Icu short-circuit level is given by the installation.

Example:


Table at 400 V AC - 3 phases 50 Hz for standard equipment.

| Reactive power (kVAR) | Inc (A) | Inb (A) | Breaking capacity to Circuit Breaker 30 kA |
|-----------------------|---------|---------|--|
| 7.5 | 11 | 16 | LV510930 |
| 10 | 14 | 20 | LV510931 |
| 15 | 22 | 30 | LV510933 |
| 20 | 29 | 40 | LV510934 |
| 30 | 43 | 60 | LV510936 |
| 40 | 58 | 80 | LV510937 |
| 50 | 72 | 100 | LV510938 |


EasyPact CVS100BS**With TM-D thermal magnetic trip unit**

EasyPact CVS100BS (25 kA at 380/415 V)


| Rating | 3P3d | 4P3d |
|--------|----------|----------|
| TM16D | LV510930 | |
| TM20D | LV510931 | |
| TM25D | LV510932 | LV510952 |
| TM32D | LV510933 | LV510953 |
| TM40D | LV510934 | LV510954 |
| TM50D | LV510935 | LV510955 |
| TM63D | LV510936 | LV510956 |
| TM80D | LV510937 | LV510957 |
| TM100D | LV510938 | LV510958 |

Connection accessories**Cable lugs**


| | | | |
|------|---------------------------------------|----------|-------------------|
| ≤50A | Cables from 2.5 to 16 mm ² | Set of 2 | EZALUG0502 |
| | | Set of 3 | EZALUG0503 |




| | | | |
|-------|--------------------------------------|----------|-------------------|
| > 50A | Cables from 10 to 50 mm ² | Set of 2 | EZALUG1002 |
| | 24V | Set of 3 | EZALUG1003 |

Spreaders

| | | |
|--------------------------|----------|------------------|
| Spreaders for 3P breaker | Set of 3 | EZASPDR3P |
| Spreaders for 4P breaker | Set of 4 | EZASPDR4P |

Terminal shields

| | | |
|---------------------------------|----------|------------------|
| Terminal shields for 3P breaker | Set of 2 | EZATSHD3P |
| Terminal shields for 4P breaker | Set of 2 | EZATSHD4P |

Phase barriers

| | | |
|----------------|----------|-----------------|
| Phase barriers | Set of 2 | EZAFASB2 |
|----------------|----------|-----------------|

Electrical auxiliaries**Indication contacts**

| | |
|-----------------------|----------------|
| Auxiliary switch (AX) | EZAUX10 |
|-----------------------|----------------|



| | |
|-------------------|----------------|
| Alarm switch (AL) | EZAUX01 |
|-------------------|----------------|




| | |
|---|----------------|
| Auxiliary switch + alarm switch (AX + AL) | EZAUX11 |
|---|----------------|

Electrical auxiliaries(Cont.)**Voltage releases**


| | Voltage | |
|----|----------|----------------------------|
| AC | 100-130V | MX/SHT |
| | 200-277V | EZASHT100AC |
| | 380-480V | EZASHT200AC |
| DC | 24V | EZASHT380AC EZASHT024DC |

Shunt trip(SHT)


| | Voltage | |
|----|----------|-----------------------|
| AC | 110-130V | MN/UVR EZAUVR200AC |

Undervoltage release(UVR)**Rotary handles****Direct rotary handle (for 3/4P breaker)**


| | |
|-------------------------------|----------|
| Direct rotary handle(black) | EZAROTDS |
|-------------------------------|----------|

Extended rotary handle (for 3/4P breaker)

| | |
|---------------------------------|---------|
| Extended rotary handle(black) | EZAROTE |
|---------------------------------|---------|

Locks**Padlocking system**




| | |
|-------------------|---------|
| Padlocking system | EZALOCK |
|-------------------|---------|

Installation accessory**DIN rail adaptor**



| | |
|--|---------|
| For 2 x 1P or 1 x 2P or 1 x 3P breaker | EZADINR |
|--|---------|

Note: for 4P breaker, use 2 adaptors




Dimensions




Backplate mounting




DIN rail mounting




Front panel cutout (small)




Front panel cutout (large)




Terminal shield




Interphase barrier



Direct rotary handle



Extended rotary handle





<https://sid1.hu/>

Schneider Electric Industries SAS

35, rue Joseph Monier
CS 30323
92506 Rueil Malmaison Cedex
France

RCS Nanterre 954 503 439
Capital social 928 298 512 €
www.se.com

Aug-2020

© 2019 - Schneider Electric. All Rights Reserved.
All trademarks are owned by Schneider Electric Industries SAS or its affiliated companies.
Document reference LVED210011EN

This document has been
printed on recycled paper

